

## NTE15004 Integrated Circuit Remote Control Preamplifier

**Description:**

This NTE15004 is a silicon monolithic integrated circuit in an 8-Lead SIP type package designed for a remote control preamplifier of infrared signals. This device features low power, high sensitivity and wide supply voltage.

**Features:**

- Wide Operation Voltage:  $V_{CC} = 6V$  to  $14.4V$
- Low Power Consumption:  $I_{CC} = 2.5mA$  typ.
- High Input Sensitivity:  $50\mu V_{p-p}$  typ.
- Peak Detector
- Small Size Package – 8-Lead SIP
- Minimum Number of External Parts Required

**Absolute Maximum Ratings:** ( $T_A = +25^\circ C$  unless otherwise specified)

Supply Voltage,  $V_{CC}$  ..... 15V  
 Power Dissipation,  $P_D$  ..... 270mW  
 Operating Temperature Range,  $T_{opr}$  .....  $-20^\circ$  to  $+75^\circ C$   
 Storage Temperature Range,  $T_{stg}$  .....  $-40^\circ$  to  $+125^\circ C$

**Recommended Operating Conditions:**

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Power Supply	$V_{CC}$		6.0	8.5	14.4	V
Input Frequency	$f_{in}$		30	–	50	kHz

**Electrical Characteristics:** ( $T_A = +25^\circ C$ ,  $V_{CC} = 8.5V$ ,  $f_{in} = 40kHz$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Supply Current	$I_{CC}$		1.5	2.5	3.5	mA
Input Terminal Voltage	$V_{IN1}$		2.1	2.6	3.1	V
	$V_{IN2}$	$I_{IN} = 70\mu A$	3.4	4.1	4.9	V
1 <sup>st</sup> Stage Voltage Gain	$A_{VL}$	Pin7 – Pin4, $V_{OUT} = 500mV_{P-P}$	–	60	–	dB
Detection Input Voltage	$V_{IN}$		–	50	100	$\mu V$
Input Impedance	$r_{in}$		40	60	80	k $\Omega$
Output Voltage	$V_{OL}$	$I_{OL} = 0.1mA$ , $V_{IN} = 1mV_{P-P}$	–	–	0.5	V
Output Leakage Current	$I_{OH}$	$V_{OH} = 14.4V$	–	–	2	$\mu A$
Noise		Input Open	Output Pin is Not Fall			

### Pin Connection Diagram (Front View)

