



## NTE15007 Integrated Circuit TV Stereo Multiplexing Decoder

### **Description:**

The NTE15007 is a bipolar integrated circuit is a 42-Lead DIP type package designed for use in TV stereo multiplexing decoding, filters for stereo, and SAP (Separate Audio Program) demodulation applications.

### **Features:**

- Low number of external parts
- Excellent channel separation characteristics for stereo applications. Min. 46dB at 1kHz.
- Selection of individual modes of MAIN/SAP/BOTH.
- Direct driving mode for LED display.

### **Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$ unless otherwise specified)

Power Supply Voltage, $V_{CC}$ .....	17V
Allowed Power Dissipation, $P_D$ .....	1800mW
Individual Controlling Pins, $V_{14 \text{ to } 17}, V_{20}$ .....	$V_{CC} + 0.3V$
LED Driving Current, $I_{LED}$ .....	25mA
Operating Temperature Range, $T_{opr}$ .....	-10° to +65°C
Storage Temperature Range, $T_{stg}$ .....	-55° to +150°C

### **Recommended Operating Condition:**

Power Supply Voltage, $V_{CC}$ .....	9.0 ± 0.5V
--------------------------------------	------------

### **Electrical Characteristics:** ( $V_{CC} = 9V$ , dBs = 0.775V<sub>rms</sub>, $T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
SAP Noise Level	$V_{SAP,N}$	Pin1 Input $5f_H$ (-14.4dBs) Pin25 Output 15kHz LPF is attached.	-	-40	-36	dB
SAP Carrier Leakage	$CL_{SAP}$	Pin1 Input $5f_H$ (-14.4dBs) Pin25 Output	-	-33	-30	dB
SAP Carrier Detecting Sensitivity	$SCARR$	Pin1 Input $5f_H$ Input level during LED of Pin18 is lighting on	-29.0	-25.0	-21.5	dB
SAP Frequency Characteristics 10kHz	$A_{SAP}$	Pin1 Input SAP 10kHz 100% (-14.4dBs) Pin25 Output 15kHz IPF is attached	-4.0	-1.5	2.0	dB

**Electrical Characteristics (Cont'd):** ( $V_{CC} = 9V$ ,  $\text{dBs} = 0.775V_{rms}$ ,  $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
SAP Output Level	$V_{SAP}$	Pin1 Input SAP 1kHz 100% (-14.4dBs) Pin25 Output 15kHz LPF is attached	-0.8	-0.1	0.6	dB
SAP Distortion Ratio	$\text{THD}_{SAP}$	Pin1 Input SAP 1kHz 100% (-14.4dBs) Pin25 Output 15kHz LPF is attached	-	4.0	8.0	%
SAP BPF Frequency Characteristics $5f_H$	A BPF $5f_H$	Pin1 Input $5f_H$ (-14.4dBs) Pin6 Output	-16	-13.5	-12.5	dB
SAP BPF Frequency Characteristics $3f_H$	A BPF $3f_H$	Pin1 Input $3f_H$ (-14.4dBs) Pin6 Output	-	-32.5	-29.5	dB
SAP BPF Frequency Characteristics $6.5f_H$	A BPF $6.5f_H$	Pin1 Input $6.5f_H$ (-14.4dBs) Pin6 Output	-	-31.6	-29.5	dB
SAP Detecting Characteristics	$V_{SAP \text{ FM}}$	Pin8 Input 63.37kHz (-14.4dBs) 93.67kHz (-14.4dBs) Pin25 Output	100	110	118	mV/kHz
SAP Muting Attenuation Amount	$\text{AT}_{SAP}$	Pin8 Input SAP 1kHz 100% (-14.4dBs) Pin25 Output	-	-68	-65	dB
MONAURAL Noise Level	$V_{ST \text{ NM}}$	Non-input Pin23 Output 15kHz LPF is attached	-	-75	-70	dB
STEREO Noise Level	$V_{ST \text{ NS}}$	Pin1 $f_H$ (-24dBs) Pin40 to Pin41 -6dB ATT Pin24 Output 15kHz LPF is attached	-	-70	-66	dB
MAIN Output Level	$V_{MAIN}$	Pin1 Input 1kHz (-10dBs) 75μs de-emphasis is attached Pin23 Output 15kHz LPF is attached	-5.6	-5.0	-4.6	dB
SUB Detecting Level	$V_{SUB}$	Pin1 Input SUB 1kHz 100% Pin40 to Pin41 -6dB ATT Pin24 Output 15kHz LPF is attached	-12	-	-9	dB
MONAURAL Distortion Ratio	$\text{THD}_{MONO}$	Pin1 Input 1kHz (-10dBs) Pin23 Output 15kHz LPF is attached	-	0.25	0.50	%
STEREO Distortion	$\text{THD}_{STE}$	Pin1 Input SUB 1kHz 100% Pin24 Output 15kHz LPF is attached	-	0.75	1.20	%
Pilot Cancel (L + R)	$PC_{L+R}$	Pin1 Input $f_H$ (-24dBs) 75μs de-emphasis is attached Pin23 Output $f_H$ BPF is attached	-	-57.0	-51.5	dB
Pilot Cancel (L - R)	$PC_{L-R}$	Pin1 Input $f_H$ (-24dBs) Pin40 to Pin41 -6dB ATT Pin24 Output $f_H$ BPF is attached	-	-41	-35	dB

**Electrical Characteristics (Cont'd):** ( $V_{CC} = 9V$ ,  $\text{dBs} = 0.775V_{rms}$ ,  $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
MAIN Balance Between Channels	$CB_{MAIN}$	Pin34 Input $f_H$ (-18dBs) Input 1kHz (-4dBs) to Pin28 and find the output level difference between Pin22 and Pin23 by measuring the outputs of Pin22 and Pin23 independently	-0.3	0	0.3	dB
SUB Balance Between Channels	$CB_{SUB}$	Input 1kHz (-4dBs) to Pin27 and find the output level difference between Pin22 and Pin23 by measuring the outputs of Pin22 and Pin23 independently. The above applicable to Pin28 except that non-input to Pin28.	-0.3	0	0.3	dB
Separation Check 1kHz	$SEP_{1k}$	Pin1 input L Ch 100% DSB 1kHz Measure phase difference between the outputs of Pin24 and Pin23.	46	60	-	dB
Crosstalk $(L - R) \leftrightarrow (SAP)$	$CT_{L-R SAP}$	Pin26 and Pin41 Input 1kHz (-4dBs) Pin24 Output +1kHz BPF	-	-80	-67	dB
Crosstalk $L \leftrightarrow SAP$	$CT_{LSAP}$	Pin27 and Pin28 Output 1kHz (-4dBs) Pin23 Output +1kHz BPF	-	-80	-74	dB
Crosstalk $R \leftrightarrow SAP$	$CT_{RSAP}$	Pin27 and Pin28 Input 1kHz (-4dBs) Pin22 Output +1kHz BPF	-	-80	-74	dB
Stereo LPF Frequency Characteristics ( $6f_H$ )	$ALP1 6f_H$	Pin1 Input $6f_H$ (-10dBs) Pin37 Output	-	-45	-36	dB
$(L + R)$ LPF Frequency Characteristics (12kHz)	$ALP2 12k$	Pin34 Input 12kHz (-4dBs) Pin29 Output	-5.2	-4.3	-2.8	dB
$(L + R)$ LPF Frequency Characteristics ( $2f_H$ )	$ALP2 2f_H$	Pin34 Input $2f_H$ (-4dBs) Pin29 Output	-	-52	-43	dB
$L - R$ LPF Frequency Characteristics (12kHz)	$ALP3 12k$	Pin26 Input 12kHz (-4dBs) Pin24 Output	-6.5	-5.3	-4.0	dB
$L - R$ LPF Frequency Characteristics ( $2f_H$ )	$ALP3 2f_H$	Pin26 Input $2f_H$ (-4dBs) Pin24 Output	-	-52	-43	dB
Stereo Capture Range LOW	$CR_{LO}$	Pin34 Input $f_H$ vicinity (-18dBs) Measure the input frequency when the LED of Pin19 goes on and off by changing the burst signal frequency	-	-	14.95	kHz
Stereo Capture Range HIGH	$CR_{HI}$	Pin35 and Pin36, $1\mu\text{F}$ and $4.7\mu\text{F}$ $560\Omega$	16.52	-	-	kHz

**Electrical Characteristics (Cont'd):** ( $V_{CC} = 9V$ ,  $\text{dBs} = 0.775V_{rms}$ ,  $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
During Forced Monaural Crosstalk (L)	$CT_L$	Pin27 Input 1kHz (-4dBs) Pin23 Output +1kHz BPF	—	-80	-74	dB
During Forced Monaural Crosstalk (R)	$CT_R$	Pin27 Input 1kHz (-4dBs) Pin22 Output +1kHz BPF	—	-80	-74	dB
Muting SW V15 High Muting Attenuation Amount (L) (R)	$AT_{ST\ L}$	Pin27 Input 1kHz (-4dBs) Pin22 and Pin23 Output +15kHz LPF	—	-80	-74	dB
DC Offset Voltage while Muting and Stereo are turned on	$VO_{MU\ ST}$	During no-input	-50	5	50	mV
DC Offset Voltage while Muting and SAP are turned on	$VO_{MU\ SAP}$	During no-input	-120	-20	120	mV
DC Offset Voltage while SAP and Monaural are turned on	$VO_{SAP\ MO}$	During no-input	-50	0	50	mV
DC Offset Voltage while SAP and Stereo are turned on	$VO_{SAP\ ST}$	During no-input	-120	0	120	mV
DC Offset Voltage while Stereo and Monaural are turned on	$VO_{ST\ MO}$	During no-input	-120	-20	120	mV
Circuit Current	$I_{CC}$	Value of inflowing current into Pin42	25	36	48	mA
$V_{14}$ , $V_{15}$ , $V_{16}$ and $V_{17}$ Controlling Voltage (L)	$V_{XL}$		GND	—	1.0	V
$V_{14}$ , $V_{15}$ , $V_{16}$ , and $V_{17}$ Controlling Voltage (H)	$V_{X\ H}$		2.5	—	$V_{CC}$	V
$V_{13}$ and $V_{20}$ Controlling Voltage (L)	$V_{Z\ L}$		GND	—	1.0	V
$V_{13}$ and $V_{20}$ Controlling Voltage (M)	$V_{Z\ M}$		2.5	—	5.5	V
$V_{13}$ and $V_{20}$ Controlling Voltage (H)	$V_{Z\ H}$		8.0	—	$V_{CC}$	V
Stereo Discriminating Level	$STE\ V_{th}$	Pin30 and Pin31 10 $\mu\text{F}$ $f_H$ level is variable	12	26	39	$\text{mV}_{rms}$
Regulator Voltage	$V_{REG}$	Pin9 DC	6.7	—	—	V

**Note 1.** This device is for **REPLACEMENT ONLY!** No design information is available.

### Pin Connection Diagram

MPX Input	1	42	V <sub>CC</sub>
N.C.	2	41	(L+R) Switch Input
Stereo Filter Adjust	3	40	(L+R) Detector Output
SAP Filter Adjust	4	39	TP
Bias	5	38	N.C.
SAP BPF Output	6	37	Stereo LPF Output
N.C.	7	36	Phase Det (+)
SAP Detector Input	8	35	Phase Det (-)
Reg Out 6.7V	9	34	Stereo Input
SAP VCO Adjust	10	33	Stereo GND
Car Det	11	32	ST VCO Adjust
SAP GND	12	31	Pilot Det (+)
SAP SQU Inhibit	13	30	Pilot Det (-)
SAP Mute	14	29	L+R Output
Mute	15	28	Matrix L+R Input
MS 1	16	27	Matrix L+R/SAP Input
MS 0	17	26	SAP Switch Input
SAP Ind Drive	18	25	SAP Det Output
Stereo Ind Drive	19	24	(L+R) SAP Output
Forced Monaural	20	23	Line Output L
LED GND	21	22	Line Output R

