



AKD4353

Evaluation board Rev.A for AK4353

GENERAL DESCRIPTION

The AKD4353 is an evaluation board for AK4353, 96kHz 24bit D/A converter with DIT. The AKD4353 has a digital interface with AKM's wave generator using ROM data and AKM's A/D converter evaluation boards. Therefore, it is easy to evaluate the AK4353.

■ Ordering guide

AKD4353 --- Evaluation board for AK4353
 (Cable for connecting with printer port of IBM-AT compatible PC and control software are packed with this.)

FUNCTION

- On-board clock generator
- Compatible with 2 types of interface
 - Direct interface with AKM's A/D converter evaluation boards and direct interface with AKM's signal generator(AKD43XX) by 10pin header
 - On-board CS8414 as DIR which accepts optical input
- BNC connector for external clock input
- 10pin header for serial control interface
- On-board mute circuit for analog output
- Optical output for TX output




Figure 1. AKD4353 Block Diagram

* Circuit diagram and PCB layout are attached at the end of this manual.

■ External analog circuit

J1(AOUTL) and J2(AOUTR) are used. The analog output signal range is nominally 3.1Vpp@5V. It is proportional to AVDD ($V_{out}=0.62 \times AVDD$).

■ Operation sequence

1) Set up the power supply lines.

- [AVDD] (red) = 2.7~5.5V : for AVDD of AK4353
- [3V] (orange) = 2.7~5.5V : for DVDD of AK4353
- [5V] (red) = 3.4~5.5V : for logic
- [AGND] (black)= 0V : for analog ground (including AVSS and DVSS of AK4353)
- [DGND] (black)= 0V : for logic ground

Each supply line should be distributed from the power supply unit.


2) Set up the evaluation mode, jumper pins and DIP switches. (See the followings.)

3) Power on.

The AK4353 should be reset once bringing SW1(-PD) "L" upon power-up.

4) Connect PORT2 with PC.

Connect PORT2 with printer port (parallel port) of IBM-AT compatible PC by 10-line flat cable packed with the AKD4353. Take care of the direction of connector. There is a mark at 1pin. The direction of PORT2 is as the following figure.




5) Set up the software.

Use the software named "AKD4353 Control Program" packed with the AKD4353.

■ Evaluation mode


1) Using A/D converted data <default>

PORT3 (ADC/ROM) is used to interface with various AKM's A/D converter evaluation boards. In case of using external clock through a BNC connector (J4), select BNC on JP14 (CLK) and short JP15 (XTE).



2) Ideal sine wave generated by ROM data

Digital signals generated by AKD43XX are used. PORT3 (ADC/ROM) is used to interface with AK43XX. Master clock is sent from AKD4353 to AKD43XX and LRCK, BICK, SDTI are supplied from AKD43XX to AKD4353. In case of using external clock through a BNC connector (J4), select “BNC” on JP14 (CLK) and short JP15 (XTE).



3) DIR(CS8414)

PORT4 (TORX174) is used for the evaluation using such as test disk. The DIR generates MCKI, BICK, LRCK, SDTI from the received data through optical connector. In this case, the EXT bit of AK4353 should be “1” (External clock mode). Select “RCA” or “OPT” on JP16 (RCA/OPT) in case of using RCA connector (J3) or optical connector (PORT4: TORX174).



■ Clock (MCLK,BICK,LRCK) set up

In case of using evaluation mode 1), JP9,10 and 17 should be set up as follows. They need no care for other evaluation mode.

MCLK	JP9 (X_MCLK)	JP10 (X_LRCK)	BICK	JP17 (X_BICK)	
128fs	x1	x1/128	32fs 64fs 128fs	x1/4 x1/2 x1	default
256fs	x1	x1/256	32fs 64fs 128fs	x1/8 x1/4 x1/2	
512fs	x2	x1/256	32fs 64fs 128fs	x1/8 x1/4 x1/2	
1024fs	x4	x1/256	32fs 64fs 128fs	x1/8 x1/4 x1/2	

Table 1. Clock set up

■ DIP switch (SW2) set up

No.1 to 5 set the mode of AK4353 and No.6 to 8 set the mode of CS8414.

No.	Pin	OFF <default>	ON
1	CAD1	Chip address (2bit)	
2	CAD0		
3	I2C	3-wire serial	I2C bus
4	TTL	CMOS level	TTL level
5	TST	-	always "ON"
6	M2	Digital interface format of CS8414 (See table 3.) (Note)	
7	M1		
8	M0		

Table 2. DIP switch set-up

(Note: M2-0 should be selected at only evaluation mode 3.
In other mode, these should be "OFF".)

Mode	Format	M2	M1	M0	JP9	DIF2	DIF1	DIF0
0	16bit, LSB justified	1	0	1	THR	0	0	0
1	18bit, LSB justified	1	1	0	THR	0	0	1
2	20bit, LSB justified	-	-	-	-	0	1	0
3	24bit, LSB justified	-	-	-	-	0	1	1
4	24bit, MSB justified	0	0	0	INV	1	0	0
5	I2S	0	1	0	THR	1	0	1

Table 3. Digital interface format set-up

(Note: 1="ON", 0="OFF".

DIF2-0 should be selected by serial control.

CS8414 does not correspond to 20/24bit LSB justified format.)

■ Serial control mode

The AK4353 can be controlled via the printer port (parallel port) of IBM-AT compatible PC. Connect PORT2 (CTRL) with PC by 10-line flat cable packed with the AKD4353.

There are two modes: 3-wire serial & I2C bus. JP4 should be shorted at 3-wire serial control mode.

Chip address can be selected by SW2(MODE)-No.1(CAD1) and No.2(CAD0).

■ Other jumper pins set up

[JP1](GND): Analog ground and digital ground

Open: Separated <default>

Short: Common (The connector "DGND" can be open.)

[JP2](5V-3V): DVDD of AK4353 and power supply to logic

Open: Independent <default>

Short: Same (The connector "3V" should be open.)

[JP3](DVDD): DVDD of AK4353

3V: Independent of AVDD <default>

AVDD: Same as AVDD (The connector "3V" can be open.)

[JP5](DZF): Mute circuit

ON: Used (Analog output is muted when DZF="H".) <default>

OFF: Not used

[JP11](SDTI): SDTI of AK4353

DATA: Data is input <default>

GND: "0" data is input

■ The function of the toggle SW (SW1)

Upper-side is "H" and lower-side is "L".

[SW1] (-PD): Resets the AK4353. Keep "H" during normal operation.

■ The indication content for LED

[LED1] (VERF): Monitors VERF pin of the CS8414. LED turns on when some error has occurred to CS8414.

[LED2] (PREM): Indicates whether the input data is pre-emphasis or not.

LED turns on when the data is pre-emphasised.

MEASUREMENT RESULTS

[Measurement condition]

- Measurement unit : ROHDE & SCHWARZ, UPD04
- MCLK : 256fs
- BICK : 64fs
- fs : 44.1kHz, 96kHz
- BW : 20Hz~20kHz (fs=44.1kHz), 20Hz~40kHz (fs=96kHz)
- Bit : 24bit
- Power Supply : AVDD=DVDD=5V, 3V
- Interface : DIR (fs=44.1kHz), Serial Multiplex (fs=96kHz)
- Temperature : Room

fs=44.1kHz

Parameter	Input signal	Measurement filter	5V	3V
S/(N+D)	1kHz, 0dB	20kLPF	97.0dB	93.6dB
DR	1kHz, -60dB	20kLPF	99.0dB	94.6dB
		20kLPF, A-weighted	102.3dB	97.9dB
S/N	no signal	20kLPF	99.0dB	94.6dB
		20kLPF, A-weighted	102.3dB	97.9dB

fs=96kHz

Parameter	Input signal	Measurement filter	5V	3V
S/(N+D)	1kHz, 0dB	40kLPF	92.5dB	90.8dB
DR	1kHz, -60dB	40kLPF	97.0dB	92.6dB
		20kLPF, A-weighted	101.5dB	97.1dB
S/N	no signal	40kLPF	97.0dB	92.6dB
		20kLPF, A-weighted	101.5dB	97.1dB

[Measurement condition]

- Measurement unit : Audio Precision, System two, Cascade
- MCLK : 256fs
- BICK : 64fs
- fs : 44.1kHz, 96kHz
- BW : 10Hz~20kHz (fs=44.1kHz), 10Hz~40kHz (fs=96kHz)
- Bit : 24bit
- Power Supply : AVDD=DVDD=5V, 3V
- Interface : DIR
- Temperature : Room

fs=44.1kHz

Parameter	Input signal	Measurement filter	5V	3V
S/(N+D)	1kHz, 0dB	20kLPF	97.4dB	93.8dB
DR	1kHz, -60dB	20kLPF	98.8dB	94.3dB
		22kLPF, A-weighted	101.6dB	97.3dB
S/N	no signal	20kLPF	98.6dB	94.3dB
		22kLPF, A-weighted	101.8dB	97.3dB

fs=96kHz

Parameter	Input signal	Measurement filter	5V	3V
S/(N+D)	1kHz, 0dB	40kLPF	94.5dB	91.5dB
DR	1kHz, -60dB	40kLPF	96.9dB	92.2dB
		22kLPF, A-weighted	101.9dB	97.3dB
S/N	no signal	40kLPF	96.8dB	92.2dB
		22kLPF, A-weighted	101.9dB	97.3dB

■ Plots

[Measurement condition]

- Measurement unit : Audio Precision, System two
- MCLK : 256fs
- BICK : 64fs
- fs : 44.1kHz, 96kHz
- Bit : 24bit
- Power Supply : AVDD=DVDD=5V
- Interface : DIR
- Temperature : Room

[Contents]

1. fs=44.1kHz

- Figure 1-1. THD+N vs. Input level
- Figure 1-2. THD+N vs. Input frequency
- Figure 1-3. Linearity
- Figure 1-4. Frequency response
- Figure 1-5. Cross-talk
- Figure 1-6. FFT (1kHz, 0dBFS)
- Figure 1-7. FFT (1kHz, -60dBFS)
- Figure 1-8. FFT (noise floor)
- Figure 1-9. FFT (out-of-band noise, ~130kHz)

2. fs=96kHz

- Figure 2-1. THD+N vs. Input level
- Figure 2-2. THD+N vs. Input frequency
- Figure 2-3. Linearity
- Figure 2-4. Frequency response
- Figure 2-5. FFT (1kHz, 0dBFS)
- Figure 2-6. FFT (1kHz, -60dBFS)
- Figure 2-7. FFT (noise floor)

AKM

AK4353 THD+N vs Input Level (AVDD=DVDD=5V, fs=44.1kHz, fin=1kHz)




Figure 1-1. THD+N vs. Input level

AKM

AK4353 THD+N vs fin (AVDD=DVDD=5V, fs=44.1kHz, Input Level=0dBFS)




Figure 1-2. THD+N vs. Input frequency

AKM

AK4353 Linearity (AVDD=DVDD=5V, fs=44.1kHz, fin=1kHz)




Figure 1-3. Linearity

AKM

AK4353 Frequency Response (AVDD=DVDD=5V, fs=44.1kHz, Input Level=0dBFS)




Figure 1-4. Frequency response

AKM

AK4353 Cross-talk (AVDD=DVDD=5V, fs=44.1kHz, Input Level=0dBFS)




Figure 1-5. Cross-talk

AKM

AK4353 FFT (AVDD=DVDD=5V, fs=44.1kHz, fin=1kHz, Input Level=0dBFS)
FFT points=16384, Avg=8, Window=Equirriple




Figure 1-6. FFT (1kHz, 0dBFS)

AKM

AK4353 FFT (AVDD=DVDD=5V, fs=44.1kHz, fin=1kHz, Input Level=-60dBFS)
FFT points=16384, Avg=8, Window=Equiripple




Figure 1-7. FFT (1kHz, -60dBFS)

AKM

AK4353 FFT (AVDD=DVDD=5V, fs=44.1kHz, No signal input)
FFT points=16384, Avg=8, Window=Equiripple




Figure 1-8. FFT (noise floor)

AKM

AK4353 FFT (Outband noise ~130kHz; AVDD=DVDD=5V, fs=44.1kHz, No signal input)
FFT points=16384, Avg=8, Window=Equiripple




Figure 1-9. FFT (out-of-band noise)

AKM

AK4353 THD+N vs Input Level (AVDD=DVDD=5V, fs=96kHz, fin=1kHz)




Figure 2-1. THD+N vs. Input level

AKM

AK4353 THD+N vs fin (AVDD=DVDD=5V, fs=96kHz, Input Level=0dBFS)




Figure 2-2. THD+N vs. Input frequency

AKM

AK4353 Linearity (AVDD=DVDD=5V, fs=96kHz, fin=1kHz)




Figure 1-3. Linearity

AKM

AK4353 Frequency Response (AVDD=DVDD=5V, fs=96kHz, Input Level=0dBFS)




Figure 1-4. Frequency response

AKM

AK4353 FFT (AVDD=DVDD=5V, fs=96kHz, fin=1kHz, Input Level=0dBFS)
FFT points=16384, Avg=8, Window=Equirriple




Figure 2-5. FFT (1kHz, 0dBFS)
Upper: Notch OFF, Lower: Notch ON

AKM

AK4353 FFT (AVDD=DVDD=5V, fs=96kHz, fin=1kHz, Input Level=-60dBFS)
FFT points=16384, Avg=8, Window=Equirriple




Figure 2-6. FFT (1kHz, -60dBFS)

AKM

AK4353 FFT (AVDD=DVDD=5V, fs=96kHz, No signal input)
FFT points=16384, Avg=8, Window=Equiripple




Figure 2-7. FFT (noise floor)

AKD4353 Control Program ver 2.0 operation manual

1. Connect IBM-AT compatible PC with AKD4353 by 10-line type flat cable (packed with AKD4353).
Take care of the direction of 10pin Header (Refer to manual of AKD4353).
2. Start up "WINDOWS 95" or "WINDOWS 98".
3. Insert the floppy-disk labeled "AKD4353 Control Program ver 2.0" into the floppy-disk drive.
4. Set up "MS-DOS" from start menu.
5. Change directory to the floppy-disk drive(ex.a:) at MS-DOS prompt.
6. Type "ak4353".
7. Then follow the displayed comment (See the following).

```
===== <<Operating flow>> =====  
Input Control Mode (3-wire serial or I2C bus)  
Input Chip Address (2bit)  
Write data/ Display register map/ Reset etc.  loop  
=====
```

At first the following message is displayed:

```
***** AK4353 Control Program ver 2.0 , '00/2 *****
copyright(c) 2000, Asahi Kasei Microsystems co.,ltd.
      All rights reserved.

Input control mode
  0: 3-wire Serial, 1: I2C Bus
:
```

Input 0 or 1.

Then the following is displayed:

```
Input Chip Address(CAD1,CAD0) (2 figure, binary) =
```

Input chip address in 2 figures of binary.

Set CAD1 and CAD0 before the AKD4353 is powered up.

When hanging CAD1 and CAD0, set SW1(-PD) "L", then "H" after that.

After chip address is defined, the following default register map is displayed (Loop starts from here):

```
3-wire Serial control mode      CAD1-0=00 -----
ADDR = 00 : 0B <Control 1> ( 0   0   0   0   DIF2 DIF1 DIF0 RSTN )
ADDR = 01 : 01 <Control 2> ( 0   0   DFS1 DFS0 CKS2 CKS1 CKS0 RSTN )
ADDR = 02 : 94 <Control 3> ( PL3  PL2  PL1  PL0  DEM1 DEM0 ATC  SMUTE )
ADDR = 03 : FF <Lch ATT>   ( ATT7  ATT6  ATT5  ATT4  ATT3  ATT2  ATT1  ATT0 )
ADDR = 04 : FF <Rch ATT>   ( ATT7  ATT6  ATT5  ATT4  ATT3  ATT2  ATT1  ATT0 )
ADDR = 05 : 00 <TX>        ( 0     0     0     0     0     0     V     TXE )
ADDR = 06 : 00 <Ch Status 1>( 0     CS29  CS28  CS24  CS3   CS2   CS2   CS1 )
ADDR = 07 : 04 <Ch Status 2>( CS15  CS14  CS13  CS12  CS11  CS10  CS9   CS8 )

Input 1(Write), R(Reset), T(Table), I(Increment), D(Decrement) or S(Stop) :
```

1) If you input "1", you can write data to AK4353.

```
You can write data to AK4353
Input Register Address (2 figure, hex) (00-07) =
```

Input register address in 2 figures of hexadecimal.

Then current data of this address is displayed:

```
ADDR = 00 : 0B <Control 1> ( 0   0   0   0   DIF2 DIF1 DIF0 RSTN )
                          0   0   0   0   1   0   1   1
Input Register Data      (2 figure, hex) (00-FF) =
```


You can write control data to this address. Input control data in 2 figures of hexadecimal.

Refer to datasheet of AK4353.


Then the data written to this address is displayed:

```
ADDR = 00 : 09 <Control 1> ( 0   0   0   0   DIF2 DIF1 DIF0 RSTN )
                          0   0   0   0   1   0   0   1
```


- 2) If you input "R" or "r", this program writes default data to all register addresses.
- 3) If you input "T" or "t", current register map is displayed.
- 4) If you input "I" or "i", this program increment data of current address by 1 (only for addr=03H or 04H). You can increment ATT value by 1step.
- 5) If you input "D" or "d", this program decrement data of current address by 1 (only for addr=03H or 04H). You can decrement ATT value by 1step.
- 6) If you input "S" or "s", this program is terminated.




Title		
AKD4353		
Size	Document Number	Rev
A4	AK4353	A
Date:	Monday, November 15, 1999	Sheet 1 of 2




Title		
AKD4353		
Size	Document Number	Rev
A3	Interface	A
Date:	Monday, November 15, 1999	Sheet 2 of 2



L1 リジスタシク AKD4363 Rev.A



L1 部品面 AKD4363 Rev.A



TS 板图 KDN383 Rev.1

IMPORTANT NOTICE

- These products and their specifications are subject to change without notice. Before considering any use or application, consult the Asahi Kasei Microsystems Co., Ltd. (AKM) sales office or authorized distributor concerning their current status.
- AKM assumes no liability for infringement of any patent, intellectual property, or other right in the application or use of any information contained herein.
- Any export of these products, or devices or systems containing them, may require an export license or other official approval under the law and regulations of the country of export pertaining to customs and tariffs, currency exchange, or strategic materials.
- AKM products are neither intended nor authorized for use as critical components in any safety, life support, or other hazard related device or system, and AKM assumes no responsibility relating to any such use, except with the express written consent of the Representative Director of AKM. As used here:
 - (a) A hazard related device or system is one designed or intended for life support or maintenance of safety or for applications in medicine, aerospace, nuclear energy, or other fields, in which its failure to function or perform may reasonably be expected to result in loss of life or in significant injury or damage to person or property.
 - (b) A critical component is one whose failure to function or perform may reasonably be expected to result, whether directly or indirectly, in the loss of the safety or effectiveness of the device or system containing it, and which must therefore meet very high standards of performance and reliability.
- It is the responsibility of the buyer or distributor of an AKM product who distributes, disposes of, or otherwise places the product with a third party to notify that party in advance of the above content and conditions, and the buyer or distributor agrees to assume any and all responsibility and liability for and hold AKM harmless from any and all claims arising from the use of said product in the absence of such notification.