

SPECIFICATION SHEET

JFW MODEL 50PA-521

BENCHTOP PROGRAMMABLE ATTENUATOR ASSEMBLY

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	200-6000 MHz
Configuration	Eight individually controlled solid-state programmable attenuators
Impedance	50 Ohms nominal
Attenuation Range	0-95 dB in 1 dB steps
VSWR	2.0:1 maximum
Attenuation Accuracy (guaranteed monotonic)	± 0.50 dB 1-3 dB ± 0.75 dB 4-7 dB ± 1.00 dB 8-11 dB ± 1.25 dB or 4% 12-95 dB (whichever is greater)
Insertion Loss	8.0 dB typical
RF Input Power	+20 dBm average +25 dBm (no damage)
Switching Speed	1 microsecond typical (after command is received and processed) (3 milliseconds typical processing time)
AC Supply	100-240 VAC @ 47-63 Hz
Manual Control	20-Button Keypad and LCD display
Remote Control	RS-232 (9600, 19200, or 38400 Baud) Ethernet (TCP, 10/100, up to 4 users)
Remote Commands	Attenuator Control Commands: Set Attenuator, Set Attenuator with Response, Read Attenuator, Set All Attenuators, Read All Attenuators, Set Multiple Attenuator, Fade Attenuator, Variable Handover, Store, Recall System Commands: Identification, Pause -RS-232 Only: Change Baud -Ethernet Only: Disconnect, Close, Message, Clear

--CONTINUED--

