

RD30LDT595

8-bit Serial-in Parallel-out LED Driver IC

REJ03D0906-0200

Rev.2.00

Jun 16, 2008

Description

The RD30LDT595 has eight edge trigger D-type Flip-Flops with eight latches in 16-pin package. Data is input to the serial data input and the clock pulse is input to the clock input. When the clock is changed from "L" to "H", the signal of the data input enters an internal shift register. The data of the shift register is shifted one by one. In addition, output load circuit is added so that power supply prevents a wrong action in on/off. When V_{CC} is less than a fixed level, the output ($\overline{Q1}$ to $\overline{Q8}$) compulsorily is off state. Low-voltage and high-speed operation is suitable for battery-powered product (e.g., notebook computers), and the low-power consumption extends the battery life.


Features

- Supply voltage range : 4.5 to 5.5 V, $V_O = 30V$
- Output current : $I_O = 100 \text{ mA}$ (@ $V_{CC} = 5 \text{ V}$)
- All the logical input has hysteresis voltage for the slow transition.
- Input with pull-up resistance. ($\overline{\text{Enable}}$, Latch terminal)
- Input with pull-down resistance. (CLK, S-in terminal)
- Ordering Information


Part Name	Package Type	Package Code (Previous Code)	Package Abbreviation	Taping Abbreviation (Quantity)	Surface Treatment
RD30LDT595PT0	DILP-16 pin	PRDP0016AE-B (DP-16FV)	P	T (1,000 pcs/reel)	0 (Ni/Pd/Au)
RD30LDT595FPH0	SOP-16 pin	PRSP0016DH-B (FP-16DAV)	FP	H (2,000 pcs/reel)	0 (Ni/Pd/Au)

Note: Please consult the sales office for the above package availability.

Pin Arrangement



Logic Diagram



Function Table

Inputs				Outputs	
S-in	CLK ^{*1}	Latch	Enable	Q1 to Q8	S-out
L	IN	L	L	t - 1	L
L	IN	H	L	Z	L
H	IN	L	L	t - 1	H
H	IN	H	L	L	H
H	IN	H	H	Z	H

*1 IN : Input the following signal in CLK



H : High level

L : Low level

Z : High impedance

t - 1 : Output level before the indicated steady state input conditions were established.

Absolute Maximum Ratings

Item	Symbol	Ratings	Unit	Test Conditions
Supply voltage range	V_{CC}	-0.5 to 7	V	
Input voltage range	V_I	-0.5 to $V_{CC} + 0.5$	V	
Output voltage range ^{*1}	V_O	-0.5 to 30	V	Output : Z (OFF)
		-0.5 to $V_{CC} + 0.5$	V	S-out
Continuous output current	I_O	100	mA	$V_O = 0$ to V_{CC}
Maximum power dissipation at $T_a = 25^\circ\text{C}$ (in still air) ^{*2}	P_d	1.19	W	DILP
		0.79		SOP
Storage temperature	T_{stg}	-65 to 150	$^\circ\text{C}$	

Notes: The absolute maximum ratings are values which must not individually be exceeded, and furthermore no two of which may be realized at the same time.

1. This value is limited to 30 V maximum.
2. The maximum package power dissipation was calculated using a junction temperature of 150 $^\circ\text{C}$.

Recommended Operating Conditions

Item	Symbol	Min	Max	Unit	Conditions		
Supply voltage range	V_{CC}	4.5	5.5	V			
Output voltage range	V_O	—	30	V	$\overline{Q1}$ to $\overline{Q8}$: Z (OFF)		
Output current (per pin)	I_O	0	100	mA	DILP	Duty cycle \leq 100%	$\overline{Q1}$ to $\overline{Q8}$: ON
		0	100	mA	SOP	Duty cycle \leq 60%	
Operating free-air temperature	T_a	-40	85	$^\circ\text{C}$			

Note: Unused or floating inputs must be held high or low.

Electrical Characteristic

Item	Symbol	V_{CC} (V) *	$T_a = 25^\circ\text{C}$			$T_a = -40$ to 85°C			Unit	Test condition
			Min	Typ	Max	Min	Typ	Max		
Input voltage	V_{IH}	4.5 to 5.5	2.0	—	V_{CC}	2.0	—	V_{CC}	V	
	V_{IL}	4.5 to 5.5	0	—	0.8	0	—	0.8	V	
Input current	I_{IH}	5.5	—	—	25	—	—	30	μA	$V_{IH} = 5.5$ V
	I_{IL}	5.5	—	—	-25	—	—	-30	μA	$V_{IL} = 0$ V
Output voltage (S-out)	V_{OH}	5.0	4.9	—	—	4.9	—	—	V	$I_{OH} = -1$ μA
	V_{OL}	5.0	—	—	0.1	—	—	0.1	V	$I_{OL} = 1$ μA
Output voltage ($\overline{Q1}$ to $\overline{Q8}$)	V_{OL}	5.0	—	—	0.55	—	—	0.77	V	$I_{OL} = 100$ mA
Output leakage current	I_{OLK}	5.5	—	—	50	—	—	100	μA	$V_O = 30$ V (Output : Z (OFF))
Quiescent supply current	I_{CC1}	5.5	—	—	300	—	—	500	μA	Input : Open All driver output : OFF
	I_{CC2}	5.5	—	—	300	—	—	500	μA	Driver output one circuit : ON
Driver output wrong action protection voltage	V_{T+}	—	2.9	3.4	3.9	2.6	3.4	4.2	V	
	V_{T-}	—	2.6	3.1	3.6	2.3	3.1	3.9	V	

Note: For conditions shown as Min or Max, use the appropriate values under recommended operating conditions.

Timing Characteristics

($V_{CC} = 5\text{ V}$, $C_L = 15\text{ pF}$, $R_L(\text{S-out}) = \infty$, $R_L(\overline{\text{Qn}}) = 100\ \Omega$, $t_r = t_f = 20\text{ ns}$)


Item	Symbol	$T_a = 25^\circ\text{C}$			$T_a = -40\text{ to }85^\circ\text{C}$			Unit	Test condition
		Min	Typ	Max	Min	Typ	Max		
Maximum clock frequency	f_{max}	—	—	12.5	—	—	12.5	MHz	Duty cycle = 45 % to 55 %
Pulse width	t_w	30	—	—	30	—	—	ns	CLK
Pulse width	t_w	30	—	—	30	—	—	ns	Latch
Setup time	t_{su}	30	—	—	30	—	—	ns	S-in to CLK
Hold time	t_h	20	—	—	20	—	—	ns	S-in to CLK
Setup time	t_{su}	60	—	—	60	—	—	ns	Latch to CLK
Clock pulse rise time	t_r	—	—	500	—	—	500	ns	
Clock pulse fall time	t_f	—	—	500	—	—	500	ns	

Switching Characteristics

($V_{CC} = 5\text{ V}$, $C_L = 15\text{ pF}$, $R_L(\text{S-out}) = \infty$, $R_L(\overline{\text{Qn}}) = 100\ \Omega$, $t_r = t_f = 20\text{ ns}$)


Item	Symbol	$T_a = 25^\circ\text{C}$			$T_a = -40\text{ to }85^\circ\text{C}$			Unit	FROM (Input)	TO (Output)
		Min	Typ	Max	Min	Typ	Max			
Propagation delay time	t_{PLH}	—	—	60	—	—	60	ns	CLK	S-out
	t_{PHL}	—	—	60	—	—	60			
	t_{PLH}	—	—	70	—	—	70	ns	CLK	$\overline{\text{Qn}}$
	t_{PHL}	—	—	70	—	—	70			
	t_{PLH}	—	—	70	—	—	70	ns	$\overline{\text{Enable}}$	$\overline{\text{Qn}}$
	t_{PHL}	—	—	70	—	—	70			

Test Circuit




Waveforms

• Waveform – 1




• Waveform – 2




- Notes 1. Input waveform : PRR \leq 1 MHz, $Z_o = 50 \Omega$, $t_r \leq 20$ ns, $t_f \leq 20$ ns
 2. The output are measured one at a time with one transition per measurement.

Application Data


Duty Cycle – Output Current Characteristics




Duty Cycle – Output Current Characteristics



Duty Cycle – Output Current Characteristics




Duty Cycle – Output Current Characteristics



Package Dimensions


JEITA Package Code	RENESAS Code	Previous Code	MASS[Typ.]
P-DIP16-6.3x19.2-2.54	PRDP0016AE-B	DP-16FV	1.05g



Reference Symbol	Dimension in Millimeters		
	Min	Nom	Max
e ₁	—	7.62	—
D	—	19.2	20.32
E	—	6.3	7.4
A	—	—	5.06
A ₁	0.51	—	—
b _p	0.40	0.48	0.56
b ₃	—	1.30	—
c	0.19	0.25	0.31
θ	0°	—	15°
e	2.29	2.54	2.79
Z	—	—	1.12
L	2.54	—	—

(Ni/Pd/Au plating)

JEITA Package Code	RENESAS Code	Previous Code	MASS[Typ.]
P-SOP16-5.5x10.06-1.27	PRSP0016DH-B	FP-16DAV	0.24g



NOTE:
 1. DIMENSIONS**1 (Nom)**AND**2* DO NOT INCLUDE MOLD FLASH.
 2. DIMENSION**3*DOES NOT INCLUDE TRIM OFFSET.

Terminal cross section
(Ni/Pd/Au plating)

Detail F

Reference Symbol	Dimension in Millimeters		
	Min	Nom	Max
D	—	10.06	10.5
E	—	5.50	—
A ₂	—	—	—
A ₁	0.00	0.10	0.20
A	—	—	2.20
b _p	0.34	0.40	0.46
b ₁	—	—	—
c	0.15	0.20	0.25
c ₁	—	—	—
θ	0°	—	8°
HE	7.50	7.80	8.00
Ⓜ	—	1.27	—
x	—	—	0.12
y	—	—	0.15
Z	—	—	0.80
L	0.50	0.70	0.90
L ₁	—	1.15	—

Notes:

1. This document is provided for reference purposes only so that Renesas customers may select the appropriate Renesas products for their use. Renesas neither makes warranties or representations with respect to the accuracy or completeness of the information contained in this document nor grants any license to any intellectual property rights or any other rights of Renesas or any third party with respect to the information in this document.
2. Renesas shall have no liability for damages or infringement of any intellectual property or other rights arising out of the use of any information in this document, including, but not limited to, product data, diagrams, charts, programs, algorithms, and application circuit examples.
3. You should not use the products or the technology described in this document for the purpose of military applications such as the development of weapons of mass destruction or for the purpose of any other military use. When exporting the products or technology described herein, you should follow the applicable export control laws and regulations, and procedures required by such laws and regulations.
4. All information included in this document such as product data, diagrams, charts, programs, algorithms, and application circuit examples, is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas products listed in this document, please confirm the latest product information with a Renesas sales office. Also, please pay regular and careful attention to additional and different information to be disclosed by Renesas such as that disclosed through our website. (<http://www.renesas.com>)
5. Renesas has used reasonable care in compiling the information included in this document, but Renesas assumes no liability whatsoever for any damages incurred as a result of errors or omissions in the information included in this document.
6. When using or otherwise relying on the information in this document, you should evaluate the information in light of the total system before deciding about the applicability of such information to the intended application. Renesas makes no representations, warranties or guarantees regarding the suitability of its products for any particular application and specifically disclaims any liability arising out of the application and use of the information in this document or Renesas products.
7. With the exception of products specified by Renesas as suitable for automobile applications, Renesas products are not designed, manufactured or tested for applications or otherwise in systems the failure or malfunction of which may cause a direct threat to human life or create a risk of human injury or which require especially high quality and reliability such as safety systems, or equipment or systems for transportation and traffic, healthcare, combustion control, aerospace and aeronautics, nuclear power, or undersea communication transmission. If you are considering the use of our products for such purposes, please contact a Renesas sales office beforehand. Renesas shall have no liability for damages arising out of the uses set forth above.
8. Notwithstanding the preceding paragraph, you should not use Renesas products for the purposes listed below:
 - (1) artificial life support devices or systems
 - (2) surgical implantations
 - (3) healthcare intervention (e.g., excision, administration of medication, etc.)
 - (4) any other purposes that pose a direct threat to human lifeRenesas shall have no liability for damages arising out of the uses set forth in the above and purchasers who elect to use Renesas products in any of the foregoing applications shall indemnify and hold harmless Renesas Technology Corp., its affiliated companies and their officers, directors, and employees against any and all damages arising out of such applications.
9. You should use the products described herein within the range specified by Renesas, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas shall have no liability for malfunctions or damages arising out of the use of Renesas products beyond such specified ranges.
10. Although Renesas endeavors to improve the quality and reliability of its products, IC products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Please be sure to implement safety measures to guard against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other applicable measures. Among others, since the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
11. In case Renesas products listed in this document are detached from the products to which the Renesas products are attached or affixed, the risk of accident such as swallowing by infants and small children is very high. You should implement safety measures so that Renesas products may not be easily detached from your products. Renesas shall have no liability for damages arising out of such detachment.
12. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written approval from Renesas.
13. Please contact a Renesas sales office if you have any questions regarding the information contained in this document, Renesas semiconductor products, or if you have any other inquiries.



RENESAS SALES OFFICES

<http://www.renesas.com>

Refer to "<http://www.renesas.com/en/network>" for the latest and detailed information.

Renesas Technology America, Inc.
450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology (Shanghai) Co., Ltd.
Unit 204, 205, AZIACenter, No.1233 Lujiazui Ring Rd, Pudong District, Shanghai, China 200120
Tel: <86> (21) 5877-1818, Fax: <86> (21) 6887-7858/7898

Renesas Technology Hong Kong Ltd.
7th Floor, North Tower, World Finance Centre, Harbour City, Canton Road, Tsimshatsui, Kowloon, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2377-3473

Renesas Technology Taiwan Co., Ltd.
10th Floor, No.99, Fushing North Road, Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 3518-3399

Renesas Technology Singapore Pte. Ltd.
1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001

Renesas Technology Korea Co., Ltd.
Kukje Center Bldg. 18th Fl., 191, 2-ka, Hangang-ro, Yongsan-ku, Seoul 140-702, Korea
Tel: <82> (2) 796-3115, Fax: <82> (2) 796-2145

Renesas Technology Malaysia Sdn. Bhd
Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No.18, Jln Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia
Tel: <603> 7955-9390, Fax: <603> 7955-9510