

NON-ISOLATED DC/DC CONVERTERS

12V Input / Programmable Output / 30A VRM 9.0 Compatible



V7NB-30A180 PRELIMINARY

- High efficiency means less power dissipation
- Remote on/off
- 2-Wire Remote sense
- Optional 5 bit voltage programming schemes
 - Intel VRM 9.x compatible 1.1V to 1.85V
 - Motorola compatible 1.0V to 1.68V
- Adaptive voltage positioning



Description

The V7NB-30A Series are non-isolated step down DC/DC converters providing up to 30A of output current and designed to be compatible to the Intel VRM 9.0 / 9.1 VID codes. Standard features include remote on/off, over current protection, remote sense and a power good signal. This product also makes use of adaptive positioning to improve transient response performance. These products are specifically design to power a wide variety of high performance microprocessors but may be used almost anywhere low-voltage silicon is being employed and a nominal 12V source is available. Typical applications include file servers, work stations and other computing applications.

Input Specifications

Parameter	Min	Typ	Max	Notes
Input Voltage Range	10.8 VDC		13.2 VDC	
Input Current (disabled)		30mA		
Input Current (full load)			6A	
Reflected Ripple Current			100mA rms	With 100uF, 25mOhm capacitor and 200nH of input inductance.

Output Specifications

Parameter	Min	Typ	Max	Notes
Output Current	0A		30A	
Set Point Accuracy	1.81V	1.83	1.85	no load, excluding Adaptive positioning, VID 00000
Adaptive Positioning (Droop Impedance)		3.33 mOhm		
Ripple and Noise		20mV		pk-pk, 0 to 20MHz Bandwidth Full load with two external 560uF oscon capacitors on output.
Turn on Time		8mS	16mS	
Transient Response				di/dt = 5A/uS
Deviation		90mV		Load step =50% of max load.
Settling Time		175uS		Cout = two 820uF OSCON
Remote Sense Compensation		±0.3VDC		
Output Capacitance	1200uF		20,000uF	For applications requiring higher or lower output capacitance please consult factory.

NON-ISOLATED DC/DC CONVERTERS

12V Input / Programmable Output / 30A VRM 9.0 Compatible



General Specifications

Parameter	Specification
Switching Frequency	1.2 MHz typical (fixed)
Dimensions	inches mm
	3.8 x 1.0 x .35 96.5 x 25.4 x 8.9
Operating Temperature	0°C to 70°C
Non-Operating Temperature	-40°C to 100°C
Protection Features	
Over current	110% to 170% max I _o
Undervoltage	UVLO V _{in} < 9.5V
Remote On/Off	Active High
Efficiency (full load)	
1.85V output	86%

Pin Connections

Row A		Row B	
Pin	Function	Pin	Function
1	VIN+	62	VIN-
2	VIN+	61	VIN-
3	VIN+	60	VIN-
4	VIN+	59	VIN-
5	Reserved	58	VRM-pres
6	No pin	57	VID4
7	VID3	56	VID2
8	VID1	55	VID0
9	TRIM	54	NC
10	PWRGD	53	OUTEN
11	VO-sen-	52	VO-sen+
12	UVLO_SET	51	Reserved
13	VO-	50	VO+
14	VO+	49	VO+
15	VO-	48	VO-
16	VO+	47	VO+
17	VO-	46	VO-
18	VO+	45	VO+
19	VO-	44	VO-
20	VO+	43	VO+
21	VO-	42	VO-
22	VO+	41	VO+
23	VO-	40	VO-
24	VO+	39	VO+
25	VO-	38	VO-
26	VO+	37	VO+
27	VO-	36	VO-
28	VO+	35	VO+
29	VO-	34	VO-
30	VO+	33	VO+
31	VO-	32	VO-

Voltage Identification (VID) Code

VID4	VID3	VID2	VID1	VID0	V _o (VDC)
1	1	1	1	1	Output Off
1	1	1	1	0	1.1
1	1	1	0	1	1.125
1	1	1	0	0	1.15
1	1	0	1	1	1.175
1	1	0	1	0	1.2
1	1	0	0	1	1.225
1	1	0	0	0	1.25
1	0	1	1	1	1.275
1	0	1	1	0	1.3
1	0	1	0	1	1.325
1	0	1	0	0	1.35
1	0	0	1	1	1.375
1	0	0	1	0	1.4
1	0	0	0	1	1.425
1	0	0	0	0	1.45
0	1	1	1	1	1.475
0	1	1	1	0	1.5
0	1	1	0	1	1.525
0	1	1	0	0	1.55
0	1	0	1	1	1.575
0	1	0	1	0	1.6
0	1	0	0	1	1.625
0	1	0	0	0	1.65
0	0	1	1	1	1.675
0	0	1	1	0	1.7
0	0	1	0	1	1.725
0	0	1	0	0	1.75
0	0	0	1	1	1.775
0	0	0	1	0	1.8
0	0	0	0	1	1.825
0	0	0	0	0	1.85

Part Numbers

There are two different models in this series based on different loop compensation for various types of capacitor banks. These models are as follows:

V7NB-30A180: Compensated for all ceramic capacitor banks consisting of 30-40 22uF ceramic capacitors

V7NB-30A18B: Compensated for capacitor bank utilizing 4-6 820uF Oscon capacitors.

V7NB-30A18M: Compensated for Oscon caps but all output voltages are divided by 1.1 yielding an effective range of 1.0 to 1.68V compatible with the requirements for new Motorola microprocessors.

©2003 Bel Fuse Inc. Specifications subject to change without notice 022103

CORPORATE

Bel Fuse Inc.
206 Van Vorst Street
Jersey City, NJ 07302
Tel 201-432-0463
Fax 201-432-9542
www.belfuse.com

FAR EAST

Bel Fuse Ltd.
8F/ 8 Luk Hop Street
San Po Kong
Kowloon, Hong Kong
Tel 852-2328-5515
Fax 852-2352-3706
www.belfuse.com

EUROPE

Bel Fuse Europe Ltd.
Preston Technology Management Centre
Marsh Lane, Suite G7, Preston
Lancashire, PR1 8UD, U.K.
Tel 44-1772-556601
Fax 44-1772-888366
www.belfuse.com