



ELECTRONICS, INC.  
44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089  
<http://www.nteinc.com>

## NTE1593 Integrated Circuit Color TV VIR Processor

### **Description:**

The NTE1593 is designed for automatic adjustment of the color saturation and tint of color television receiver.

### **Functions:**

- Identification of line 19 and the detection of the presence of a VIR signal
- The development of dc color-controlling voltage by processing the VIR portion of the receiver's simulated blue drive signal
- The development of dc tint controlling voltage by processing the VIR portion of the receiver's demodulated R-Y signal

### **Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$ unless otherwise specified)

Supply Voltage, $V_{CC}$ .....	14.4V
LED Drive Current, $I_{LED}$ .....	20mA
Power Dissipation ( $T_A = +65^\circ\text{C}$ ), $P_T$ .....	600mW
Operating Temperature Range, $T_{opt}$ .....	-10° to +65°C
Storage Temperature Range, $T_{stg}$ .....	-55° to +125°C

### **Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$ , $V_{CC} = 12\text{V}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
Current Drive	$I_{CC}$	LED OFF	-	21	35	mA	
Output Voltage of Color Control Stage	$V_{5H}$	VIR: ON	High Level	10	11.2	-	V
	$V_{5L}$		Low Level	-	0.5	1.0	V
	$V_{5H}$	VIR: OFF, Manual	High Level	-	10.7	-	V
	$V_{5L}$		Low Level	-	0	-	V
Output Voltage of Tint Control Stage	$V_{6H}$	VIR: ON	High Level	10	11.4	-	V
	$V_{6L}$		Low Level	-	0.3	1.0	V
	$V_{6H}$	VIR: OFF, Manual	High Level	-	10.7	-	V
	$V_{6L}$		Low level	-	0	-	V
Differential Voltage Gain of Color Control Stage	$G_{VD1}$	VIR: ON $R_L = 10\text{k}\Omega$	Input: Pin 3 to Pin 4 Output: Pin 5	-	40	-	dB
Differential Voltage Gain of Tint Control Stage	$G_{VD2}$		Input: Pin 4 to Pin 9 Output: Pin 6	-	3.4	-	dB

### Pin Connection Diagram

