## MADRCC0004



#### **Quad Driver for GaAs FET Switches and Attenuators**

M/A-COM Products Rev. 3

#### **Features**

- High Speed CMOS Technology
- · Complementary Outputs
- Positive Voltage Control
- Low Power Dissipation
- Plastic SOIC Package for SMT Applications
- Tape and Reel Packaging Available
- Lead-Free SOIC-16 Package
- 100% Matte Tin Plating over Copper
- Halogen-Free "Green" Mold Compound
- 260°C Reflow Compatible
- RoHS\* Compliant Version of DR65-0001

### **Description**


M/A-COM's MADRCC0004 is a Quad channel driver used to translate TTL control inputs into gate voltages for GaAs FET microwave switches and attenuators. High speed analog CMOS technology is utilized to achieve low power dissipation at moderate to high speeds, encompassing most microwave switching applications.

## **Ordering Information**

Part Number	Package		
MADRCC0004	Bulk Packaging		
MADRCC0004TR	1000 piece reel		

Note: Reference Application Note M513 for reel size information.

### **Logic Diagram**



### **Pin Configuration**

Pin No.	Function	Pin No.	Function
1	A3	9	C2
2	В3	10	C1
3	A4	11	GND
4	B4	12	GND
5	V <sub>EE</sub>	13	A1
6	V <sub>CC</sub>	14	B1
7	C4	15	A2
8	C3	16	B2

## **Guaranteed Operating Ranges**

Symbol	Parameter <sup>1</sup>	Unit	Min	Typical	Max
V <sub>CC</sub>	Positive DC Supply Voltage	V	4.5	5.0	5.5
V <sub>EE</sub>	Negative DC Supply Voltage	V	-5.5	-5.0	-4.5
T <sub>A</sub>	Operating Ambient Temperature	°C	-40	+25	+85
I <sub>OH</sub>	I <sub>OH</sub> DC Output Current - HIGH		_	_	-1.0
I <sub>OL</sub>	I <sub>OL</sub> DC Output Current - LOW		_	_	1.0
T <sub>rise</sub> , T <sub>fall</sub>	Maximum Input Rise or Fall Time	nS	_	_	500

<sup>1.</sup> All voltages are relative to GND.

- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
   Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298
- Visit www.macom.com for additional data sheets and product information.

<sup>\*</sup> Restrictions on Hazardous Substances, European Union Directive 2002/95/EC.




#### **Quad Driver for GaAs FET Switches and Attenuators**

M/A-COM Products Rev. 3

#### AC & DC Characteristics Over Guaranteed Operating Range

Symbol	Parameter	Test Co	nditions	Units	Min	Тур	Max
$V_{IH}$	Input HIGH Voltage	Guaranteed HIGH Input Voltage		V	2.0	1	-
$V_{IL}$	Input LOW Voltage	Guaranteed LO	W Input Voltage	V	-	-	0.8
$V_{OH}$	Output HIGH Voltage	I <sub>OH</sub> = -1 mA	V <sub>EE</sub> = Max	V	- 0.1	-	-
$V_{OL}$	Output LOW Voltage	I <sub>OL</sub> = 1 mA	V <sub>EE</sub> = Max	V	_	1	V <sub>EE</sub> + 0.1
I <sub>IN</sub>	Input Current	$V_{IN} = V_{CC}$ or GND	V <sub>EE</sub> = Min	μΑ	-10	0	10
I <sub>CC</sub>	Quiescent Supply Current	V <sub>CC</sub> = Max	$V_{EE} = Min$ $V_{IN} = V_{CC} \text{ or GND}$	μA	_	_	400
$\Delta I_{CC}$	Additional Supply Current, per TTL Input pin	V <sub>CC</sub> = Max	$V_{IN} = V_{CC} - 2.1V$	mA	_	_	1.0
$T_{PHL}, T_{PLH}$	Propagation Delay	Guaranteed -40° C to + 85° C		nS	_	1	50
$T_{THL}, T_{TLH}$	Output Transition Time	Guaranteed -40° C to + 85° C		nS	_	_	25
	Delay Skew, Output A to Output B	Guaranteed -40° C to + 85° C		nS	_	_	8

### **Switching Waveforms**



Note: See Switching Wave Forms for the definition of the switching terms. Supplies must be by-passed with .01  $\mu F$  Capacitors

Note: Unused inputs must be tied to Ground

## **Handling Procedures**

Please observe the following precautions to avoid damage:

### **Static Sensitivity**

Silicon Integrated Circuits are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these devices.

## **Absolute Maximum Ratings<sup>2,3</sup>**

Parameter	Absolute Maximum		
V <sub>CC</sub>	5V to + 6.0 V		
V <sub>EE</sub>	- 6.0 V to5 V		
V <sub>CC</sub> - V <sub>EE</sub>	12 V		
V <sub>IN</sub> <sup>4</sup>	V <sub>CC</sub> + .5 V		
V <sub>OUT</sub>	V <sub>EE</sub> 5 V		
Storage Temperature	-65°C to +150°C		
Operating Temperature	-40°C to +85°C		

- Exceeding any one or combination of these limits may cause permanent damage to this device.
- M/A-COM does not recommend sustained operation near these survivability limits.
- Standard CMOS TTL interface, latch-up will occur if logic signal is applied prior to power supply.

#### **Truth Table**

Input	Outputs		
C <sub>X</sub>	A <sub>X</sub>	B <sub>X</sub>	
0	V <sub>EE</sub>	GND	
1	GND	V <sub>EE</sub>	

**PRELIMINARY:** Data Sheets contain information regarding a product M/A-COM has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not quaranteed.

<sup>•</sup> North America Tel: 800.366.2266 / Fax: 978.366.2266

<sup>•</sup> Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300

Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298 Visit www.macom.com for additional data sheets and product information.


# MADRCC0004



#### **Quad Driver for GaAs FET Switches and Attenuators**

M/A-COM Products Rev. 3

#### Lead-Free, SOIC-16<sup>†</sup>



<sup>&</sup>lt;sup>†</sup> Reference Application Note M538 for lead-free solder reflow recommendations.

3

<sup>•</sup> Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300

Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298
 Visit www.macom.com for additional data sheets and product information.