

MOS FET Relays


G3VM-101AR/DR

Compact, General-purpose, Analog-switching MOS FET Relays, with 1A Switching.

- Continuous load current of 1 A
- Switches minute analog signals
- Dielectric strength of 2,500 Vrms between I/O
- RoHS Compliant

Application Examples

- Communication equipment and Measurement devices
- Security systems and Power circuits
- Factory Automation equipment



NEW

Note: The actual product is marked differently from the image shown here.

List of Models


Package Type	Contact form	Terminals	Load voltage (peak value)	Model	Number per stick	Number per tape
DIP4	SPST-NO	PCB terminals	100 V	G3VM-101AR	100	---
		Surface-mounting terminals		G3VM-101DR		
				G3VM-101DR(TR)	---	1,500

Note: The AC peak and DC value are given for the load voltage.


Dimensions

Note: All units are in millimeters unless otherwise indicated.

G3VM-101AR




G3VM-101DR





Terminal Arrangement/Internal Connections (Top View)

G3VM-101AR




G3VM-101DR



Note: The actual product is marked differently from the image shown here.


PCB Dimensions (Bottom View)

G3VM-101AR



Actual Mounting Pad Dimensions (Recommended Value, Top View)

G3VM-101DR



■ Absolute Maximum Ratings (Ta = 25°C)


Item	Symbol	Rating	Unit	Measurement conditions	
Input	LED forward current	I_F	30	mA	
	Repetitive peak LED forward current	I_{FP}	1	A	100 μ s pulses, 100 pps
	LED forward current reduction rate	$\Delta I_F/^\circ\text{C}$	-0.3	mA/°C	Ta \geq 25°C
	LED reverse voltage	V_R	5	V	
	Connection temperature	T_j	125	°C	
Output	Load voltage (AC peak/DC)	V_{OFF}	100	V	
	Continuous load current (AC peak/DC)	I_O	1	A	
	ON current reduction rate	$\Delta I_{ON}/^\circ\text{C}$	-10	mA/°C	Ta \geq 25°C
	Pulse ON current	I_{OP}	3	A	t=100 mS, Duty = 1/10
	Connection temperature	T_j	125	°C	
Dielectric strength between input and output (See note 1.)	V_{I-O}	2,500	V_{rms}	AC for 1 min	
Operating temperature	T_a	-40 to +85	°C	With no icing or condensation	
Storage temperature	T_{stg}	-55 to +125	°C	With no icing or condensation	
Soldering temperature (10 s)	---	260	°C	10 s	

Note: 1. The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side.

■ Electrical Characteristics (Ta = 25°C)

Item	Symbol	Minimum	Typical	Maximum	Unit	Measurement conditions	
Input	LED forward voltage	V_F	1.18	1.33	1.48	V	$I_F = 10$ mA
	Reverse current	I_R	---	---	10	μ A	$V_R = 5$ V
	Capacity between terminals	C_T	---	70	---	pF	$V = 0$, $f = 1$ MHz
	Trigger LED forward current	I_{FT}	---	0.5	3	mA	$I_O = 1$ A
Output	Maximum resistance with output ON	R_{ON}	---	250	700	m Ω	$I_F = 5$ mA, $I_O = 1$ A, $t < 1$ s
	Current leakage when the relay is open	I_{LEAK}	---	---	1.0	μ A	$V_{OFF} = 100$ V
	Capacity between terminals	C_{OFF}	---	200	---	pF	$V = 0$, $f = 1$ MHz
Capacity between I/O terminals	C_{I-O}	---	0.8	---	pF	$f = 1$ MHz, $V_s = 0$ V	
Insulation resistance between I/O terminals	R_{I-O}	1,000	---	---	M Ω	$V_{I-O} = 500$ VDC, $R_{OH} \leq 60\%$	
Turn-ON time	t_{ON}	---	0.8	5.0	ms	$I_F = 5$ mA, $R_L = 200 \Omega$, $V_{DD} = 20$ V (See note 2.)	
Turn-OFF time	t_{OFF}	---	0.3	1.0	ms		

Note: 2. Turn-ON and Turn-OFF Times




■ Recommended Operating Conditions

Use the G3VM under the following conditions so that the Relay will operate properly.


Item	Symbol	Minimum	Typical	Maximum	Unit
Load voltage (AC peak/DC)	V_{DD}	---	---	80	V
Operating LED forward current	I_F	5	10	25	mA
Continuous load current (AC peak/DC)	I_O	---	---	1	A
Operating temperature	T_a	-20	---	65	°C

■ Engineering Data


LED forward current vs. Ambient temperature




Continuous load current vs. Ambient temperature




LED forward current vs. LED forward voltage




Continuous load current vs. On-state voltage




On-state resistance vs. Ambient temperature




Trigger LED forward current vs. Ambient temperature




Turn ON, Turn OFF time vs. LED forward current



Turn ON, Turn OFF time vs. Ambient temperature



Current leakage vs. Ambient temperature



Precautions

Be sure to read the precautions and information common to all G3VM MOS FET relays, contained in the Technical User's Guide, "MOSFET Relays, Technical Information" for correct use.

All sales are subject to Omron Electronic Components LLC standard terms and conditions of sale, which can be found at http://www.components.omron.com/components/web/webfiles.nsf/sales_terms.html

ALL DIMENSIONS SHOWN ARE IN MILLIMETERS.
To convert millimeters into inches, multiply by 0.03937. To convert grams into ounces, multiply by 0.03527.

OMRON[®]

**OMRON ELECTRONIC
COMPONENTS LLC**

55 E. Commerce Drive, Suite B
Schaumburg, IL 60173

847-882-2288

OMRON ON-LINE

Global - <http://www.omron.com>

USA - <http://www.components.omron.com>

Cat. No. K141-E-01

07/12

Specifications subject to change without notice

Printed in USA