

# WRE\_P-3W & WRF\_P-3W Series 3W, WIDE INPUT, ISOLATED & REGULATED SINGLE/DUAL OUTPUT DIP DC-DC CONVERTER





#### multi-country patent protection RoHS

#### **FEATURES**

Efficiency Up To 82%

Operating Temperature: -40°C to +85°C

3KVDC Isolation

Short circuit protection(automatic recovery)

No external component required Internal SMD construction Industry standard pinout MTBF>1,000,000 hours UL94-V0 Package RoHS Compliance

#### **APPLICATIONS**

The WRE\_P-3W & WRF\_P-3W Series are specially designed for applications where a wide range input voltage power supplies are isolated from the input power supply in a distributed power supply system on a circuit board.

These products apply to:

- Where the voltage of the input power supply is wide range (voltage range≤2:1);
- 2) Where isolation is necessary between input and output(Isolation Voltage≤3000VDC);
- Where the regulation of the output voltage and the output ripple noise are demanded.

#### PRODUCT PROGRAM Input Output Part Efficiency Voltage (VDC) Current (mA) Voltage Number (%, Typ) (VDC) Nominal Range WRE1205P-3W ±5 +300 +30 74 WRE1209P-3W 76 ±9 ±167 ±16 WRE1212P-3W ±12 ±125 ±12 78 WRE1215P-3W 79 +15 +100 +10 12 9-18 22 WRF1205P-3W 5 600 60 74 WRF1209P-3W 9 333 33 76 WRF1212P-3W 12 250 25 78 200 WRF1215P-3W 15 20 79 WRF2405P-3W ±5 ±300 +30 78 WRE2409P-3W ±9 ±167 ±16 80 WRE2412P-3W ±12 ±125 ±12 82 WRE2415P-3W 81 ±15 ±100 ±10 18-36 40 WRF2405P-3W 5 600 60 78 WRF2409P-3W 9 333 33 80 WRF2412P-3W 12 250 25 82 WRF2415P-3W

\*Input voltage can't exceed this value, or will cause the permanent damage.

Note:The load shouldn't be less than 10%,otherwise ripple will increase dramatically.


Operation under 10% load will not damage the converter; However, they may not meet all specification listed.

ISOLATION SPECIFICATIONS					
Item	Test Conditions	Min	Тур	Max	Units
Isolation voltage	Tested for 1 minute and 1mA max	3000			VDC
Isolation resistance	Test at 500VDC	1000			МΩ

OUTPUT SPECIFICATIONS						
Item	Test Conditions	Min	Тур	Max	Units	
Output power	See below products program	ets program 0.3 3 W				
Positive voltage accuracy	Refer to recommended circuit		±1	±3		
Negative voltage accuracy	Refer to recommended circuit		±3	±5	±5 %	
Load regulation	From 10% To 100% load		±0.5	±1*		
Line regulation(at full load)	Input voltage from low to high		±0.2	±0.5		
Temperature Drift(Vout)	Refer to recommended circuit			±0.03	%/℃	
Ripple & Noise **	20MHz bandwidth		50	100	mVp-p	
Switching frequency	100% load, nominal Input voltage		300		KHz	
* Dual output models unhalans	and loads LEO/					

<sup>\*</sup> Dual output models unbalanced load: ±5%

## APPLICATIONS WRE1205P-3W



#### MORNSUN Science & Technology co.,Ltd.

Address: 2th floor 6th building, Huangzhou Industrial District, Guangzhou, China

Tel: 86-20-38601850 Fax: 86-20-38601272

Http://www.mornsun-power.com


#### Note:

- All specifications measured at T<sub>A</sub>=25°C, humidity<75%, nominal input voltage and rated output load unless otherwise specified.
- 2. See below recommended circuits for more details.


<sup>\*\*</sup>Test ripple and noise by "parallel cable" method. See detailed operation instructions at Testing of Power Converter section, application notes.

COMMON SPECIFICATION					
Item	Test Conditions	Min	Тур	Max	Units
Storage humidity				95	%
Operating temperature		-40		85	c
Storage temperature		-55		125	
Temp. rise at full load			15		
Lead temperature	1.5mm from case for 10 seconds			300	
Cooling		Free air convection			
Short circuit protection		Continuous, automatic recovery			
Case material		Plastic (UL94-V0)			
MTBF		100			K hours
Weight			17		g

#### **TYPICAL CHARECTERISTICS**



#### **OUTLINE DIMENSIONS & PIN CONNECTIONS**





Note: Unit:mm(inch)


Pin diameter: 0.50mm (0.020inch)

Pin diameter tolerances:  $\pm 0.05$ mm( $\pm 0.002$ inch) General tolerances:  $\pm 0.25$ mm( $\pm 0.010$ inch)

### First Angle Projection 🗐 🕀

RECOMMENDED FOOTPRINT Top view, grid: 2.54mm (0.1inch), diameter: 1.00mm(0.039inch)

#### Single /Dual Output



#### **FOOTPRINT DETAILS**

Pin	Single	Dual
2,3	GND	GND
9	NC	0V
11	NC	-Vo
10,15	NC	NC
14	+Vo	+Vo
16	0V	0V
22,23	Vin	Vin
NC:No	Connection	


#### **APPLICATION NOTE**

#### **Requirement On Output Load**

In order to ensure the product operate efficiently and reliably, in addition to a max load (namely full load), a minimum load is specified for this kind of DC/DC converter. Make sure the specified range of input voltage is not exceeded, the minimum output load no less than 10% load. If the actual load is less than the specified minimum load, the output ripple may increase sharply while its efficiency and reliability will reduce greatly. If the actual output power is very small, please add an appropriate resistor as extra loading, or contact our company for other lower output power products.

#### **Recommended Circuit**

All the WRE P-3W &WRF P-3W Series have been tested according to the following recommended testing circuit before leaving factory. This series should be tested under load. Never be tested under no load (see Figure 1).



If you want to further decrease the input/output ripple, you can increase capacitance properly or choose capacitors with low ESR. However, the capacitance of the output filter capacitor must be proper. If the capacitance is too big, a startup problem might arise. For every channel of output, provided the safe and reliable operation is ensured, the greatest capacitance of its filter capacitor sees (Table 1).

General: Cin: 12V 100µF 24V 10µF-47µF Cout: 10µF/100mA


. Output External Capacitor Table(Table 1)

Single Vout (VDC)	Cout (uF)	Dual Vout (VDC)	Cout (uF)
5	1000	±5	680
9	680	±9	470
12	470	±12	330
15	330	±15	220

#### **Input Current**

When it is used in unregulated power supply, be sure that the fluctuating range of the power supply and the rippled voltage do not exceed the module standard. Input current of power supply should afford the startup current of this kind of DC/DC module. (Figure 2)

General: Ip ≤1.4\*lin-max



No parallel connection or plug and play.