

# APPLIED CONCEPTS INC.

397 Route 281 - P.O. BOX 453
Tully, New York 13159-0453
Phone: (315) 696-6676 Fax: (315) 696-9923
www.acipower.com

# AC5-12-1051

### PRELIMINARY DATA SHEET

3/30/00

# **CCFL INVERTER**

(For Multiple Tube Applications)

The AC5-12-1051 is designed to power 5 CCFL's to a nominal power level of 27 watts.

Intensity control (0-100%) is accomplished by the user providing a variable dc level of 0V(off) to 5V(full-on) at pin 5 of CON1.

Enable control is accomplished at pin 3 of CON1 (0V=off, 5V=on).

All outputs are open and short circuit protected.

#### Specifications:

Vin = +12V +/- 10%

CCFL strike voltage = 1800Vrms @ Vin=12V

CCFL tube current = 7.5mA/tube @ 100% intensity/Vin=12V)

Recommended CCFL sustaining voltage = 630Vrms - 770Vrms

Nominal tube current frequency = 50khz +/- 10%

Nominal pwm frequency = 98Hz +/- 3%

Pwm duty cycle range = 0 to 100%

Average electrical efficiency >90%

External PWM signal input control via enable pin

Output PWM sync signal @ pin 6 of CON1

## Additional control capability:\*

Supports multiple units ie:Master/Slave(s)

Synchronization to display frame-rate

Low power sleep-mode and soft-start

UL 1950 approval pending

\* Please contact factory for information

