






## **TO-220 Plastic Package**

CSB857, CSB858 CSD1133, CSD1134


## CSB857, 858 PNP PLASTIC POWER TRANSISTORS CSD1133, 1134 NPN PLASTIC POWER TRANSISTORS

Low frequency Power Amplifier



**857** 

*858* 



	DIM	MIN.	MAX.
diffill Signs III filti.	Α	14.42	16.51
	В	9.63	10.67
	С	3.56	4.83
	D		0.90
	Ε	1.15	1.40
	F	3.75	3.88
	G	2.29	2.79
	Н	2.54	3.43
	J		0.56
	K	12.70	14.73
	L	2.80	4.07
	М	2.03	2.92
	N		31.24
=	0	DEG 7	

## ABSOLUTE MAXIMUM RATINGS

		<i>857</i>	8	85 <b>8</b>
		<i>1133</i>	1134	
Collector-base voltage (open emitter)	$V_{CBO}$	max. 70		70 V
Collector-emitter voltage (open base)	$V_{C\!E\!O}$	max. 50		60 V
Collector current	$I_C$	max.	4.0	$\boldsymbol{A}$
Total power dissipation up to $T_C = 25^{\circ}C$	$P_{tot}$	max.	40	W
Junction temperature	$T_{i}$	max.	<i>150</i>	${}^{\!$
Collector-emitter saturation voltage	3			
$I_C = 2 A$ ; $I_B = 200 \text{ mA}$	$V_{CEsat}$	max.	1.0	V
D.C. current gain				
$I_C = 1 A; V_{CE} = 4 V$	$h_{\!F\!E}$	min.	60	
		max.	320	

# **RATINGS** (at $T_A$ =25°C unless otherwise specified) Limiting values

		<i>1133</i>	1134
Collector-base voltage (open emitter)	$V_{CBO}$	max. 70	70 V
Collector-emitter voltage (open base)	$V_{C\!E\!O}$	max. 50	60 V
Emitter-base voltage (open collector)	$V_{EBO}$	max.	5.0 V

## CSB857, CSB858 CSD1133, CSD1134

vw.DataSheet4U.com

Collector current	$I_C$	max.	4.0	$\boldsymbol{A}$
Collector current (Peak value)	$I_C$	max.	8.0	$\boldsymbol{A}$
Total power dissipation up to $T_C = 25^{\circ}C$	$P_{tot}$	max.	40	W
Junction temperature	$T_{j}$	max.	150	${\mathscr C}$
Storage temperature	$\mathring{T}_{St\mathscr{Q}}$		−65 to +150	${\mathscr C}$

## **CHARACTERISTICS**

 $T_{amb} = 25$ °C unless otherwise specified

			<i>857</i>		<i>858</i>	
			<i>1133</i>	1134		
Collector cutoff current						
IE = 0; $VCB = 50V$		$I_{CBO}$	max.	1.0	$\mu A$	
Breakdown voltages						
$I_C = 50 \text{ mA}; I_B = 0$		$V_{CEO}$	min. 50		60 V	
$I_C = 10 \ \mu A; I_E = 0$		$V_{CBO}$	min.	70	V	
$I_E = 10 \ \mu A; I_C = 0$		$V_{EBO}$	min.	5.0	V	
Saturation voltage						
$I_C = 2 A; I_B = 0.2 A$		$V_{CEsat}^*$	max.	1.0	V	
Base emitter on voltage						
$I_C = 1 A$ ; $V_{CE} = 4 V$		$V_{BE(on)}^*$	max.	1.0	V	
D.C. current gain						
$I_C = 0.1 \text{ A}; V_{CE} = 4 \text{ V}$		hFE*	min.	35		
$I_C = 1.0 A$ ; $V_{CF} = 4 V^{**}$		$h_{\!F\!E^*}$	min.	60		
0 , 02		12	max.	320		
Transition frequency						
$I_C = 0.5 \text{ A}; V_{CE} = 4 \text{ V}$	PNP	$f_T$	typ.	15	MHz	
5 02	NPN	-	typ.	7.0	MHz	

<sup>\*\*</sup> hfe classification: B: 60-120 C: 100-200 D: 160-320

<sup>\*</sup> Pulse test

#### **Notes**

## **Disclaimer**

The product information and the selection guides facilitate selection of the CDIL's Discrete Semiconductor Device(s) best suited for application in your product(s) as per your requirement. It is recommended that you completely review our Data Sheet(s) so as to confirm that the Device(s) meet functionality parameters for your application. The information furnished on the CDIL Web Site/ CD are believed to be accurate and reliable. CDIL however, does not assume responsibility for inaccuracies or incomplete information. Furthermore, CDIL does not assume liability whatsoever, arising out of the application or use of any CDIL product; neither does it convey any license under its patent rights nor rights of others. These products are not designed for use in life saving/support appliances or systems. CDIL customers selling these products (either as individual Discrete Semiconductor Devices or incorporated in their end products), in any life saving/support appliances or systems or applications do so at their own risk and CDIL will not be responsible for any damages resulting from such sale(s).

CDIL strives for continuous improvement and reserves the right to change the specifications of its products without prior notice.



CDIL is a registered Trademark of

Continental Device India Limited

C-120 Naraina Industrial Area, New Delhi 110 028, India. Telephone + 91-11-2579 6150, 5141 1112 Fax + 91-11-2579 5290, 5141 1119

email@cdil.com www.cdilsemi.com