Old Company Name in Catalogs and Other Documents

On April 1st, 2010, NEC Electronics Corporation merged with Renesas Technology Corporation, and Renesas Electronics Corporation took over all the business of both companies. Therefore, although the old company name remains in this document, it is a valid Renesas Electronics document. We appreciate your understanding.

Renesas Electronics website: http://www.renesas.com

April 1st, 2010 Renesas Electronics Corporation Issued by: Renesas Electronics Corporation (http://www.renesas.com) Send any inquiries to http://www.renesas.com/inquiry.

Notice

- 1. All information included in this document is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas Electronics products listed herein, please confirm the latest product information with a Renesas Electronics sales office. Also, please pay regular and careful attention to additional and different information to be disclosed by Renesas Electronics such as that disclosed through our website.
- Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
- 3. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part.
- 4. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
- 5. When exporting the products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations. You should not use Renesas Electronics products or the technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations.
- 6. Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
- 7. Renesas Electronics products are classified according to the following three quality grades: "Standard", "High Quality", and "Specific". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below. You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application categorized as "Specific" without the prior written consent of Renesas Electronics. Further, you may not use any Renesas Electronics. Renesas Electronics product for any application for which it is not intended without the prior written consent of Renesas incurred by you or third parties arising from the use of any Renesas Electronics product for an application categorized as "Specific" or for which the product is not intended where you have failed to obtain the prior written consent of Renesas Electronics. The quality grade of each Renesas Electronics product is "Standard" unless otherwise expressly specified in a Renesas Electronics data sheets or data books, etc.
 - "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots.
 - "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anticrime systems; safety equipment; and medical equipment not specifically designed for life support.
 - "Specific": Aircraft; aerospace equipment; submersible repeaters; nuclear reactor control systems; medical equipment or systems for life support (e.g. artificial life support devices or systems), surgical implantations, or healthcare intervention (e.g. excision, etc.), and any other applications or purposes that pose a direct threat to human life.
- 8. You should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
- 9. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
- 10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
- 11. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics.
- 12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.
- (Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majorityowned subsidiaries.
- (Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

RENESAS HD74LVC1G66

Single Analog Switch

REJ03D0026-0300Z Rev.3.00 Jul. 01, 2004

Description


The HD74LVC1G66 has an analog switch in a 5-pin package. Switch section has its enable input control (CONT). High-level voltage applied to CONT turns on the switch section. Applications include signal gating chopping, modulation or demodulation (modem), and signal multiplexing for analog to digital to analog conversion systems. Low voltage and high-speed operation is suitable for the battery powered products (e.g., notebook computers), and the low power consumption extends the battery life.

Features

- The basic gate function is lined up as renesas uni logic series.
- Supply voltage range: 1.65 to 5.5 V Operating temperature range: -40 to +85°C
- Control input: V_{IH} (Max.) = 5.5 V (@V_{CC} = 0 V to 5.5 V)
- Ordering Information

Part Name	Package Type	Package Code	Package Abbreviation	Taping Abbreviation (Quantity)
HD74LVC1G66CPE	WCSP-5 pin	TBS-5V	CP	E (3,000 pcs/reel)
HD74LVC1G66CLE		TBS-5AV	CL	

Article Indication



Function Table


Control	Switch
L	OFF
Н	ON


H: High level

L: Low level



Pin Arrangement





Absolute Maximum Ratings

Item	Symbol	Ratings	Unit	Test Conditions
Supply voltage range	Vcc	–0.5 to 6.5	V	
Input voltage range *1	VI	-0.5 to 6.5	V	
Output voltage range *1, 2	Vo	-0.5 to V _{CC} +0.5	V	Output : H or L
Control Input clamp current	I _{IK}	-50	mA	V ₁ < 0
Output clamp current	I _{ОК}	±50	mA	$V_0 < 0 \text{ or } V_0 > V_{CC}$
Continuous output current	lo	±50	mA	$V_0 = 0$ to V_{CC}
Continuous current through V _{CC} or GND	I _{CC} or I _{GND}	±100	mA	
Package Thermal impedance	θ_{ja}	154	°C/W	СР
		132	1	CL
Storage temperature	Tstg	-65 to 150	°C	

Notes: The absolute maximum ratings are values, which must not individually be exceeded, and furthermore no two of which may be realized at the same time.

1. The input and output voltage ratings may be exceeded if the input and output clamp-current ratings are observed.

2. This value is limited to 5.5 V maximum.



Recommended Operating Conditions

ltem	Symbol	Min	Max	Unit	Conditions
Supply voltage range	V _{cc}	1.65	5.5	V	
Control Input voltage range	Vi	0	5.5	V	
Input/Output voltage range	V _{I/O}	0	Vcc	V	
Input transition rise or fall rate	$\Delta t / \Delta v$	0	20	ns / V	V _{CC} = 1.65 to 1.95 V,
					2.3 to 2.7 V
		0	10		$V_{CC} = 3.0$ to 3.6 V
		0	10		V_{CC} = 4.5 to 5.5 V
Operating free-air temperature	Ta	-40	85	°C	

Note: Unused or floating inputs must be held high or low.

Electrical Characteristics

ltem	Symbol	V _{cc} (V)	Min	Тур	Max	Unit	Test condition
Input voltage	VIH	1.65 to 1.95	V _{CC} ×0.65		-	V	
		2.3 to 2.7	V _{CC} ×0.7		-		
		3.0 to 3.6	V _{CC} ×0.7	_	-3		
		4.5 to 5.5	V _{CC} ×0.7	- /			
	V _{IL}	1.65 to 1.95	—	-	V _{cc} ×0.35		
		2.3 to 2.7	—	-	V _{cc} ×0.3		
		3.0 to 3.6	_	-	V _{cc} ×0.3		
		4.5 to 5.5	- 0	-	V _{cc} ×0.3		
On-state switch	R _{ON}	1.65	- 6	13	30	Ω	$I_S = 4 \text{ mA}$ $V_I = V_{CC} \text{ or GND}$
resistance		2.3		9	20		I _S = 8 mA
		3.0	2	7.5	15		I _S = 24 mA
		4.5	- 0	5.5	10		I _S = 32 mA
Peak on resistance	R _{ON} (P)	1.65	-	74.5	120		$I_S = 4 \text{ mA}$ $V_I = V_{CC} \text{ to GND}$
		2.3	_	20	30		I _S = 8 mA
		3.0	_	11.5	20		I _S = 24 mA
		4.5	_	7.5	15		I _S = 32 mA
Off-state switch	I _{S (OFF)}	5.5	_		±1.0	μA	$V_1 = V_{CC}$ and $V_0 = GND$ or
leakage current				—	±0.1* ¹		$V_1 = GND$ and $V_0 = V_{CC}$,
	-						$V_{\rm C} = V_{\rm IL}$
On-state switch	I _{S (ON)}	5.5		_	±1.0	μA	$V_{I} = V_{CC}$ or GND, $V_{C} = V_{IH}$
leakage current	-				±0.1* ¹		V _O = Open
Control input	I _{IN}	5.5			±1.0	μA	$V_{IN} = V_{CC} \text{ or } GND$
current					±0.1* ¹		
Quiescent	I _{CC}	5.5			10	μA	$V_{IN} = V_{CC} \text{ or } GND$
supply current					1.0* ¹		
	ΔI_{CC}	5.5	<u> </u>		500	μA	$V_{\rm C} = V_{\rm CC} - 0.6 \ V$
Control input capacitance	CIC	5.0		3.0		pF	
Switch terminal	C _{I/O(OFF)}	5.0		6.0		рF	
capacitance	CI/O(OFF) CI/O(ON)	5.0		13		- ^{P'}	

Note: 1. Ta = 25°C



Switching Characteristics

 $V_{CC} = 1.8 \pm 0.15 \text{ V}$

		Ta = -40) to 85°C			FROM	то
Item	Symbol	Min	Max	Unit	Test Conditions	(Input)	(Output)
Propagation delay time*1	t _{PLH}	_	2.0	ns	$C_{L} = 30 \text{ pF}, R_{L} = 1.0 \text{ k}\Omega$	INOUT or	OUTIN or
	t _{PHL}					OUTIN	INOUT
Enable time	t _{zH}	2.5	12.0		$C_{L} = 30 \text{ pF}, R_{L} = 1.0 \text{ k}\Omega$	CONT	INOUT or
	t _{ZL}						OUTIN
Disable time	t _{HZ}	2.2	10.0		$C_{L} = 30 \text{ pF}, R_{L} = 1.0 \text{ k}\Omega$	CONT	INOUT or
	t _{LZ}						OUTIN

 $V_{CC}=2.5\pm0.2~V$

		Ta = -40 to 85°C				FROM	TO
ltem	Symbol	Min	Max	Unit	Test Conditions	(Input)	(Output)
Propagation delay time*1	t _{PLH}	_	1.2	ns	$C_L = 30 \text{ pF}, R_L = 500 \Omega$	INOUT or	OUTIN or
	t _{PHL}					OUTIN	INOUT
Enable time	t _{zH}	1.9	6.5		$C_{L} = 30 \text{ pF}, R_{L} = 500 \Omega$	CONT	INOUT or
	t∠L						OUTIN
Disable time	t _{HZ}	1.4	6.9		$C_{L} = 30 \text{ pF}, R_{L} = 500 \Omega$	CONT	INOUT or
	t _{LZ}						OUTIN

 $V_{\rm CC} = 3.3 \pm 0.3 \, {\rm V}$

		Ta = -40) to 85°C	- / /		FROM	то
Item	Symbol	Min	Max	Unit	Test Conditions	(Input)	(Output)
Propagation delay time*1	t _{PLH}		0.8	ns	$C_{L} = 50 \text{ pF}, R_{L} = 500 \Omega$	INOUT or	OUTIN or
	t _{PHL}					OUTIN	INOUT
Enable time	t _{ZH}	1.8	5.0		$C_{L} = 50 \text{ pF}, R_{L} = 500 \Omega$	CONT	INOUT or
	t _{ZL}						OUTIN
Disable time	t _{HZ}	2.0	6.5		$C_{L} = 50 \text{ pF}, \text{ R}_{L} = 500 \Omega$	CONT	INOUT or
	t _{LZ}						OUTIN

 $V_{CC}=5.0\pm0.5~V$

		10		5		V _{CC}	$= 5.0 \pm 0.5$ V
Item	Symbol	Ta = -40 Min	to 85°C Max	Unit	Test Conditions	FROM (Input)	TO (Output)
Propagation delay time* ¹		1	0.6	ns	$C_L = 50 \text{ pF}, R_L = 500 \Omega$	INOUT or OUTIN	OUTIN or INOUT
Enable time	t _{ZH} t _{ZL}	1.5	4.2		$C_L = 50 \text{ pF}, R_L = 500 \Omega$	CONT	INOUT or OUTIN
Disable time	t _{HZ} t _{LZ}	1.4	5.0		$C_L = 50 \text{ pF}, R_L = 500 \Omega$	CONT	INOUT or OUTIN

Note: 1. The propagation delay is calculated RC time constant of typical on-state resistance of the switch and the specified load capacitance, when driven by an ideal voltage source (zero output impedance).




Analog	Switch	Characteristics
--------	--------	-----------------

		Т	a = 25°	°C				FROM	то
Item	V _{cc} (V)	Min	Тур	Max	Unit		Test conditions	(Input)	(Output)
Frequency response	1.65	—	35	—	MHz	$C_{L} = 50 \text{ pF},$	Adjust fin voltage to obtain	INOUT or	OUTIN or
(Switch ON)	2.3	—	120			$R_L = 600 \Omega$	0dBm at output when fin is	OUTIN	INOUT
· · · ·	3.0	—	175	_			1MHz (sine wave).		
	4.5	—	195	_			Increase fin frequency until		
	1.65	—	>300			$C_L = 5 \text{ pF},$	the dB–meter reads –3 dBm.		
	2.3	—	>300			$R_L = 50 \Omega$	$20 \log(V_0/V_1) = -3 \text{ dBm}$		
	3.0	—	>300						
	4.5		>300	—					
Crosstalk	1.65	—	35		mV	$C_{L} = 50 \text{ pF},$	Adjust RL value to obtain 0A	CONT	OUTIN or
(Control input to signal	2.3	—	50			$R_L = 600 \Omega$	at I _{IN/OUT} when fin is 1MHz		INOUT
output)	3.0		70	—			(square wave)		
	4.5		100	—					
Feed through	1.65	_	-58	—	dB	$C_{L} = 50 \text{ pF},$	Adjust fin voltage to obtain	INOUT or	OUTIN or
attenuation	2.3	—	-58	—	ļ	$R_L = 600 \Omega$	0dBm at input when fin is	OUTIN	INOUT
(Switch OFF)	3.0	_	-58	—			1MHz (sine–wave)		
	4.5	—	-58	—					
	1.65	—	-42	—	ļ	C∟ = 5 pF,			
	2.3	—	-42	—		$R_L = 50 \Omega$			
	3.0	—	-42	—					
	4.5	_	-42	—					
Sine-wave distortion	1.65	—	0.1	—	%	$C_{L} = 50 \text{ pF},$	V _I =1.4V _{P-P} , V _{CC} =1.65V	INOUT or	OUTIN or
	2.3		0.025			$R_L = 10 \ k\Omega$	V _I =2.0V _{P-P} , V _{CC} =2.3V	OUTIN	INOUT
	3.0	—	0.015	—		fin = 1 kHz	V _I =2.5V _{P-P} , V _{CC} =3.0V		
	4.5	—	0.01	—		(sine-wave)	V _I =4.0V _{P-P} , V _{CC} =4.5V		
	1.65	—	0.15	- (2	$C_{L} = 50 pF$,			
	2.3	—	0.025			$R_{L} = 10 k\Omega$			
	3.0	—	0.015	-1		fin = 10 kHz			
	4.5		0.01	-		(sine-wave)			

Operating Characteristics


			Ta = 25°C				
Item	Symbol	V _{cc} (V)	Min	Тур	Max	Unit	Test Conditions
Power dissipation capacitance	CPD	1.8	—	8	—	pF	f = 10 MHz
		2.5	—	9	—		
		3.3	_	9	_		
		5.0	—	11	—		

Test Circuit







Test Circuit (cont.)










RENESAS

Package Dimensions





HD74LVC1G66

TBS-5AV	
EIAJ Package Code JEDEC Code Mass (g) Lead Material 0.001	
Image: constraint of the section of	Symbol Dimension in Millimeters Min Nom Max A — 0.50 A1 0.155 0.185 A2 — (0.315 D 0.90 — E 1.40 — e 0.50 — X — 0.055 Y — 0.05
	y1 0.20 ZD 0.20 ZE 0.20



Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs! 1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

- Notes regarding these materials 1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party. 2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials. 3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.

- therefore recommended that customers contact Renessa Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
 The information described here may contain technical inaccuracies or typographical errors. Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (http://www.renesas.com).
 4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or making a final decision or the information contained herein.
 5. Renesas Technology Corp. emiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use. use.
- use. 6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials. 7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited. 8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



http://www.renesas.com

RENESAS SALES OFFICES

Renesas Technology America, Inc. 450 Holger Way, San Jose, CA 95134-1368, U.S.A Tel: <1> (408) 382-7500 Fax: <1> (408) 382-7501

Renesas Technology Europe Limited. Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, United Kingdom Tel: <44> (1628) 585 100, Fax: <44> (1628) 585 900

Renesas Technology Europe GmbH Dornacher Str. 3, D-85622 Feldkirchen, Germany Tel: <49> (89) 380 70 0, Fax: <49> (89) 929 30 11

Renesas Technology Hong Kong Ltd. 7/F., North Tower, World Finance Centre, Harbour City, Canton Road, Hong Kong Tel: <852> 2265-6688, Fax: <852> 2375-6836

Renesas Technology Taiwan Co., Ltd. FL 10, #99, Fu-Hsing N. Rd., Taipei, Taiwan Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd. 26/F., Ruijin Building, No.205 Maoming Road (S), Shanghai 200020, China Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd. 1, Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632 Tel: <65> 6213-0200, Fax: <65> 6278-8001