

SANYO Semiconductors DATA SHEET

2SK3745LS—High-Voltage, High-Speed Switching Applications

Features

- · Low ON-resistance, low input capacitance, ultrahigh-speed switching.
- · High reliability (Adoption of HVP process).
- Micaless package facilitating mounting.
- · Avalanche resistance guarantee.

Specifications

Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Conditions	Ratings	Unit
Drain-to-Source Voltage	VDSS		1500	V
Gate-to-Source Voltage	VGSS		±20	V
Drain Current (DC)	I _D *		2	Α
Drain Current (Pulse)	IDP		4	Α
Allowable Power Dissipation	D-		2.0	W
	PD	Tc=25°C	35	W
Channel Temperature	Tch		150	°C
Storage Temperature	Tstg		-55 to +150	°C
Avalanche Enargy (Single Pulse) *1	EAS		42	mJ
Avalanche Current *2	I _{AV}		2	Α

^{*}Shows chip capability

Electrical Characteristics at Ta=25°C

Parameter	Symbol	Conditions	Ratings			Linit
			min	typ	max	Unit
Drain-to-Source Breakdown Voltage	V(BR)DSS	ID=1mA, VGS=0V	1500			V
Zero-Gate Voltage Drain Current	IDSS	V _{DS} =1200V, V _{GS} =0V			100	μΑ
Gate-to-Source Leakage Current	IGSS	VGS= ±16V, VDS=0V			±10	μΑ
Cutoff Voltage	VGS(off)	V _{DS} =10V, I _D =1mA	2.5		3.5	V
Forward Transfer Admittance	yfs	V _{DS} =20V, I _D =1A	0.7	1.4		S
Static Drain-to-Source On-State Resistance	Rps(on)	ID=1A, VGS=10V		10	13	Ω

Marking: K3745 Continued on next page.

- Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.
- SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

^{*1} V_{DD}=99V, L=20mH, I_AV=2A

^{*2} L≤20mH, single pulse

2SK3745LS


Continued from preceding page.

Parameter	Symbol	Conditions		Ratings		
	Symbol		min	typ	max	Unit
Input Capacitance	Ciss	VDS=30V, f=1MHz		380		pF
Output Capacitance	Coss	V _{DS} =30V, f=1MHz		70		pF
Reverse Transfer Capacitance	Crss	VDS=30V, f=1MHz		40		pF
Turn-ON Delay Time	t _d (on)	See specified Test Circuit.		12		ns
Rise Time	t _r	See specified Test Circuit.		37		ns
Turn-OFF Delay Time	t _d (off)	See specified Test Circuit.		152		ns
Fall Time	tf	See specified Test Circuit.		59		ns
Total Gate Charge	Qg	V _{DS} =200V, V _{GS} =10V, I _D =2A		37.5		nC
Gate-to-Source Charge	Qgs	VDS=200V, VGS=10V, ID=2A		2.7		nC
Gate-to-Drain "Miller" Charge	Qgd	V _{DS} =200V, V _{GS} =10V, I _D =2A		20		nC
Diode Forward Voltage	V _{SD}	I _S =2A, V _{GS} =0V		0.88	1.2	V


Note) Although the protection diode is contained between gate and source, be careful of handling enough.

Package Dimensions


unit : mm 7509-002




Switching Time Test Circuit




Avalanche Resistance Test Circuit





2SK3745LS



- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of November, 2005. Specifications and information herein are subject to change without notice.