TOSHIBA RECTIFIER SILICON DIFFUSED TYPE

# S5277B, S5277G, S5277J, S5277N

GENERAL PURPOSE RECTIFIER APPLICATIONS

• Average Forward Current : I<sub>F (AV)</sub>=1.0A

Repetitive Peak Reverse Voltage: V<sub>RRM</sub> = 100~1000V

#### MAXIMUM RATINGS ( $Ta = 25^{\circ}C$ )

CHARACTERISTIC		COLOR CODE	SYMBOL	RATINGS	UNIT		
	S5277B		White	$ m v_{RRM}$	100	v	
Repetitive Peak Reverse Voltage	S5277G		Blue		400		
	S5277J		Yellow		600		
	S52771	V	Green		1000	1	
Average Forward Current			I <sub>F (AV)</sub>	1.0	A		
			S5277B	T	50 (50Hz)		
Forward Current (Non Repetitive)		S5277G	55 (60Hz)				
		Ş	S5277J	$I_{FSM}$	30 (50Hz)	A	
		S5277N			33 (60Hz)		
Junction Temperature			$T_{j}$	-40~150	°C		
Storage Temperature Range			$\mathrm{T_{stg}}$	-40~150	°C		

1. ANODE
2. CATHODE

JEDEC —
EIAJ DO-41

TOSHIBA 3-3C1A


Unit in mm

Weight: 0.3g

## ELECTRICAL CHARACTERISTICS (Ta = 25°C)

CHARACTERISTIC	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Peak Forward Voltage	$ m V_{FM}$	$I_{FM} = 1.0A$	_	_	1.2	V
Repetitive Peak Reverse Current	$I_{RRM}$	V <sub>RRM</sub> =Rated	_	_	10	$\mu$ <b>A</b>
Thermal Resistance (Junction to Ambient)	R <sub>th (j-a)</sub>	DC	_	_	120	°C/W

## **MARK**





### COLOR CODE


COLOR	TYPE
WHITE	S5277B
BLUE	S5277G
YELLOW	S5277J
GREEN	S5277N


961001EAA2

<sup>●</sup> TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.









The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.

The information contained herein is subject to change without notice.