2SA1398

FOR HIGH CURRENT APPLICATION SILICON PNP EPITAXIAL TYPE

DESCRIPTION

2SA1398 is a silicon PNP epitaxial type transistor designed with high collector current, small VCE(sat).


Complementary with 2SC3580.

FEATURE

- ●High collector current I cM=-1A
- ●High gain band width product ft=180MHz typ
- ●Low collector to emitter saturation voltage VcE(sat)=-0.25V typ
- Excellent linearity of DC foward current gain

APPLICATION

Small type motor drive, relay drive, power supply application.



MAXIMUM RATINGS (Ta=25°C)

Symbol	Parameter	Ratings	Unit
Vcво	Collector to Base voltage	-25	V
VEBO	Emitter to Base voltage	-4	٧
VCEO	Collector to Emitter voltage	-20	V
Ісм	Peak Collector current	-1	A
lc	Collector current	-700	mA
Pc	Collector dissipation(Ta=25℃)	900	mW
Tj	Junction temperature	+150	င
Tstg	Storage temperature	-55 to +150	°C

ELECTRIAL CHARACTERISTICS RATINGS (Ta=25°C)


Symbol	Parameter	Test conditions	Limits			1.1-14
		i est conditions	Min	Тур	Max	Unit
V(BR)CBO	C to B break down voltage	Ic=-10 μ A,IE=0	-25			V
V(BR)EBO	E to B break down voltage	IE=-10 μ A,IC=0	-4			V
V(BR)CEO	C to E break down voltage	Ic=-100 μ A,R _{BE} =∞	-20			T V
Ісво	Collector cut off current	Vcb=-25V,IE=0	· · · · · ·	<u> </u>	-1	μА
IEBO	Emitter cut off current	VEB=-2V,IC=0			-1	μA
hre *	DC forward current gain	Vce=-4V,lc=-100mA	150	<u> </u>	800	
VCE(sat)	C to E saturation voltage	Ic=-500mA,IB=-25mA		-0.25	-0.5	V
ft	Gain band width product	Vce=-6V,Ie=10mA		180		MHz

^{*:} It shows her classification in right table.


Item	E	F	G
hFE	150 to 300	250 to 500	400 to 800

FOR HIGH CURRENT APPLICATION SILICON PNP EPITAXIAL TYPE
















COMMON EMITTER OUTPUT (2)




COLLECTOR TO EMITTER VOLTAGE VCE (V)

COLLECTOR TO EMITTER VOLTAGE VCE (V)



COMMON EMITTER TRANSFER (2)



BASE TO EMITTER VOLTAGE VBE (V)



http://www.idc-com.co.jp 6-41, TSUKUBA, ISAHAYA, NAGASAKI, 854-0065, JAPAN

Keep safety in your circuit designs!

Isahaya Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of non-flammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

•These materials are intended as reference to assist out customers in the selection of the Isahaya semiconductor product best suited to the customer's application, they do not convey any license under any intellectual property rights, or any other rights, belonging to Isahaya Electronics Corporation or a third party.

Isahaya Electronics Corporation assumes no responsibility for any damage, or infringement of any third-party rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in the materials.

All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by Isahaya Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact Isahaya Electronics Corporation or authorized Isahaya Semiconductor product distributor for the latest product information before purchasing a product listed herein.

The prior written approval of Isahaya Electronics Corporation is necessary to reprint or reproduce in whole or in part these materials.

If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.

Please contact Isahaya Electronics Corporation or an authorized Isahaya Semiconductor product distributor for further details on these materials or the products contained therein.