


### **Technical Data Sheet**

## 7383/G1C3-ATVA/X/MS

#### **Features**

- Popular T-1 3/4 diameter package.
- Choice of various viewing angles.
- Available on tape and reel.
- Reliable and robust.
- ESD-withstand voltage: up to 4KV.
- The product itself will remain within RoHS compliant version.
- UV resistant epoxy



- The series is specially designed for applications requiring higher brightness.
- The LED lamps are available with different colors, intensities, epoxy colors, etc.
- Superior performance in outdoor environment

#### **Applications**

- Color Graphic Signs
- Message boards
- Variable message signs (VMS)
- Commercial outdoor advertising

#### **Device Selection Guide**

Device Number: DLE-738-037

LED Part No.	Chip Mterial	<b>Emitted Color</b>	Lens Color	Stopper
7383/G1C3-ATVA/MS	InGaN	Super Green	Water Clear	No
7383/G1C3-ATVA/P/MS	InGaN	Super Green	Water Clear	Yes

Everlight Electronics Co., Ltd. http\\:www.everlight.com Rev :1 Page: 1 of 8

Prepared date:05-26-2006 Prepared : Grace Shen






### **Technical Data Sheet**


# 7383/G1C3-ATVA/X/MS

### **Package Dimensions**


**Stopper type** 



#### No Stopper type



- ① Anode
- @ Cathode



#### **Notes:**

- All dimensions are in millimeters, tolerance is 0.25mm except being specified.
- Lead spacing is measured where the lead emerges from the package.
- Protruded resin under flange is 1.5mm Max LED.

Everlight Electronics Co., Ltd. Device Number: DLE-738-037

 $http \verb|\| : www.everlight.com|\\$ 

Prepared date:05-26-2006

Rev:1

Page: 2 of 8

Prepared: Grace Shen



### **Technical Data Sheet**

# 7383/G1C3-ATVA/X/MS

### **Absolute Maximum Ratings (Ta=25°C)**

Parameter	Symbol	Rating	Units
Forward Current	$I_{\mathrm{F}}$	30	mA
Pulse Forward Current*1	$I_{FP}$	100	mA
Operating Temperature	$T_{opr}$	-40 ~ +85	$^{\circ}\!\mathbb{C}$
Storage Temperature	$T_{stg}$	-40 ~ +100	$^{\circ}\!\mathbb{C}$
Electrostatic Discharge	ESD	4K	V
Soldering Temperature*2	$T_{sol}$	260 ±5	$^{\circ}\!\mathbb{C}$
Power Dissipation	$P_d$	120	mW
Zener Reverse Current	Iz	100	mA
Reverse Voltage	$V_R$	5	V

**Notes:** \*1: $I_{FP}$  Conditions--Pulse Width  $\leq$  10msec and Duty  $\leq$  1/10.

### **Electro-Optical Characteristics (Ta=25°C)**

		<u> </u>				
Parameter	Symbol	Condition	Min.	Тур.	Max.	Units
Forward Voltage	$V_{\mathrm{F}}$	I <sub>F</sub> =20mA	2.8		3.6	V
Zener Reverse Voltage	Vz	I <sub>Z</sub> =5mA	5.2			V
Luminous Intensity	$I_V$	I <sub>F</sub> =20mA	7150		14250	mcd
Viewing Angle	2 0 1/2	I <sub>F</sub> =20mA		30		deg
Peak Wavelength	λр	I <sub>F</sub> =20mA		518		nm
Dominant Wavelength	λd	I <sub>F</sub> =20mA	524	528	532	nm
Spectrum Radiation Bandwidth	Δλ	I <sub>F</sub> =20mA		35		nm
Reverse Current	$I_R$	V <sub>R</sub> =5V			50	μΑ

Everlight Electronics Co., Ltd. http\\:www.everlight.com Rev:1 Page: 3 of 8

Device Number: DLE-738-037 Prepared date:05-26-2006 Prepared: Grace Shen

<sup>\*2:</sup>Soldering time ≤ 5 seconds.



### **Technical Data Sheet**

# 7383/G1C3-ATVA/X/MS

Rank Combination (I<sub>F</sub>=20mA)

Rank	T	U	V
Luminous Intensity	7150~9000	9000~11250	11250~14250

<sup>\*</sup>Measurement Uncertainty of Luminous Intensity: ±15%

Unit: :mcd

Rank	0	1	2	3
Forward Voltage	2.8~3.0	3.0~3.2	3.2~3.4	3.4~3.6

<sup>\*</sup>Measurement Uncertainty of Forward Voltage: ±0.1V

Unit:V

Rank	1	2
Dominant Wavelength	524~528	528~532

<sup>\*</sup>Measurement Uncertainty of Dominant Wavelength ±1.0nm

Unit:nm

Everlight Electronics Co., Ltd. http\\:www.everlight.com Rev :1 Page: 4 of 8

Device Number: DLE-738-037 Prepared date:05-26-2006 Prepared: Grace Shen


<sup>\*</sup>The quantity ratio of the ranks is decided by EVERLIGHT.





### **Technical Data Sheet**


## 7383/G1C3-ATVA/X/MS


### **Typical Electro-Optical Characteristics Curves**














Page: 5 of 8

Everlight Electronics Co., Ltd. http\\:www.everlight.com Rev:1 Device Number: DLE-738-037

Prepared date:05-26-2006 Prepared: Grace Shen



### **Technical Data Sheet**

## 7383/G1C3-ATVA/X/MS

#### **Packing Quantity Specification**

1.500PCS/1Bag, 5Bags/1Box

2.10Boxes/1Carton

#### **Label Form Specification**

CPN: Customer's Production Number

P/N: Production Number OTY: Packing Quantity

CAT: Ranks of Luminous Intensity and Forward Voltage

HUE: Ranks of Dominant Wavelength

**REF:** Reference

LOT No: Lot Number

MADE IN TAIWAN: Production Place

Everlight Electronics Co., Ltd. http\\:www.everlight.com Rev :1 Page: 6 of 8

Device Number : DLE-738-037 Prepared date:05-26-2006 Prepared : Grace Shen




### **Technical Data Sheet**

### 7383/G1C3-ATVA/X/MS

#### **Notes**

- 1. Above specification may be changed without notice. EVERLIGHT will reserve authority on material change for above specification.
- 2. When using this product, please observe the absolute maximum ratings and the instructions for using outlined in these specification sheets. EVERLIGHT assumes no responsibility for any damage resulting from use of the product which does not comply with the absolute maximum ratings and the instructions included in these specification sheets.
- 3. These specification sheets include materials protected under copyright of EVERLIGHT corporation. Please don't reproduce or cause anyone to reproduce them without EVERLIGHT's consent.
- 4. Below the zener reference voltage Vz, all the current flows through LED and as the voltage rises to Vz, the zener diode "breakdown." If the voltage tries to rise above Vz current flows through the zener branch to keep the voltage at exactly Vz.
- 5. When the LED is connected using serial circuit, if either piece of LED is no light up but current can't flow through causing others to light down. In new design, the LED is parallel with zener diode. if either piece of LED is no light up but current can flow through causing others to light up.



Everlight Electronics Co., Ltd. http\\:www.everlight.com Rev :1 Page: 7 of 8

Device Number : DLE-738-037 Prepared date:05-26-2006 Prepared : Grace Shen



### **Technical Data Sheet**

## 7383/G1C3-ATVA/X/MS

#### 6. Soldering Condition

Careful attention should be paid during soldering. When soldering, leave more then 3mm from solder joint to case, and soldering beyond the base of the tie bar is recommended.

Avoiding applying any stress to the lead frame while the LEDs are at high temperature particularly when soldering.

Recommended soldering conditions:

Hand Soldering		DIP Soldering		
Temp. at tip of iron	400°C Max. (30W Max.)	Preheat temp.	100°C Max. (60 sec Max.)	
Soldering time	3 sec Max.	Bath temp.	265 Max.	
Distance	3mm Min.(From solder joint to case)	Bath time.	5 sec Max.	
		Distance	3mm Min.	

EVERLIGHT ELECTRONICS CO., LTD.

Office: No 25, Lane 76, Sec 3, Chung Yang Rd,

Tucheng, Taipei 236, Taiwan, R.O.C

Tel: 886-2-2267-2000, 2267-9936

Fax: 886-2267-6244, 2267-6189, 2267-6306

http:\\www.everlight.com

Everlight Electronics Co., Ltd. http\\:www.everlight.com Rev :1 Page: 8 of 8

Device Number: DLE-738-037 Prepared date:05-26-2006 Prepared: Grace Shen