## HR311A 311AMHz One-Port SAW Resonator



Approved by:

Checked by:

Issued by:

# **SPECIFICATION**

PRODUCT: SAW RESONATOR MODEL: HR311 TO-39


## HOPE MICROELECTRONICS CO., LIMITED

Tel:+86-755-82973806 Fax:+86-755-82973550 E-mail: <u>sales@hoperf.com</u> http://www.hoperf.com Page 1 of 1

**HR311A** 

The HR311A is a true one-port, surface-acoustic-wave (SAW) resonator in a low-profile metal TO-39 case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at **311.000** MHz.

#### 1.Package Dimension (TO-39)




2.Marking

### **HR311A**

Color: Black or Blue


#### **4.Typical Application Circuits**

1) Low-Power Transmitter Application




#### 5. Typical Frequency Response

▶1:Transmission /H Log Mag ▶2:Off 5.0 dB/ Ref -1.58 dB




Pin	Configuration			
1	Input / Output			
2	Output / Input			
3	Case Ground			
Dimension	Data (unit: mm)			
А	9.30±0.20			
В	5.08±0.10			
С	3.40±0.20			
D	3±0.20 / 5±0.20			
E	0.45±0.20			


**3.Equivalent LC Model and Test Circuit** 



#### 2) Local Oscillator Application



#### **6.Temperature Characteristics**



The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

#### 7.Performance

#### 7-1.Maximum Ratings

Rating	Value	Unit	
CW RF Power Dissipation	Р	0	dBm
DC Voltage Between Any two Pins	V <sub>DC</sub>	± 30	V
Storage Temperature Range	$T_{\rm stg}$	-40 to +85	
Operating Temperature Range	T <sub>A</sub>	-10 to +60	

#### 7-2. Electronic Characteristics

	Characteristic	Sym	Minimum	Typical	Maximum	Unit
Center Frequency (+25)	Absolute Frequency	f <sub>C</sub>	310.925		311.075	MHz
	Tolerance from 311.000MHz	$\Delta f_{C}$		± 75		kHz
Insertion Loss		IL		1.5	2.2	dB
Quality Factor	Unloaded Q	QU		12,500		
	50 $\Omega$ Loaded Q	QL		1,800		
Temperature Stability	Turnover Temperature	T <sub>0</sub>	25		55	
	Turnover Frequency	f <sub>0</sub>		f <sub>C</sub>		kHz
	Frequency Temperature Coefficient	FTC		0.032		ppm/ <sup>2</sup>
Frequency Aging Absolute Value during the First Year		f <sub>A</sub>		10		ppm/yr
DC Insulation Resistance Between Any Two Pins			1.0			MΩ
RF Equivalent RLC Model	Motional Resistance	R <sub>M</sub>		19	29	Ω
	Motional Inductance	L <sub>M</sub>		120.3114		μH
	Motional Capacitance	C <sub>M</sub>		2.1240		fF
	Pin 1 to Pin 2 Static Capacitance	C <sub>0</sub>	2.45	2.75	3.05	pF

#### **(i)**CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

#### C 2003. All Rights Reserved.

- 1. The center frequency,  $f_c$ , is measured at the minimum IL point with the resonator in the 50 test system.
- 2. Unless noted otherwise, case temperature  $T_C = +25^{\circ}C \pm 2^{\circ}C$ .
- Frequency aging is the change in f<sub>c</sub> with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature,  $T_0$ , is the temperature of maximum (or turnover) frequency,  $f_0$ . The nominal frequency at any case temperature,  $T_c$ , may be calculated from:  $f = f_0 [1 FTC (T_0 T_c)^2]$ .
- This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C<sub>0</sub> is the measured static (nonmotional) capacitance between Pin1 and Pin2. The measurement includes case parasitic capacitance.
- 6. Derived mathematically from one or more of the following directly measured parameters:  $f_c$ , IL, 3 dB bandwidth,  $f_c$  versus  $T_c$ , and  $C_0$ .
- 7. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.
- 10. For questions on technology, prices and delivery, please contact our sales offices or e-mail sales@hoperf.com.