




Product Description

Stanford Microdevices' SXL-189 amplifier is a high efficiency GaAs Heterojunction Bipolar Transistor (HBT) MMICs housed in low-cost surface-mountable plastic package. These HBT MMICs are fabricated using molecular beam epitaxial growth technology which produces reliable and consistent performance from wafer to wafer and lot to lot.

These amplifiers are specially designed for use as driver devices for infrastructure equipment in the 800-1000 MHz cellular bands.

Its high linearity make it an ideal choice for multi-carrier as well as digital applications.



SXL-189

800-1000 MHz 50 Ohm **Power MMIC Amplifier**



Product Features

- Patented High Reliability GaAs HBT **Technology**
- High Linearity Performance: +42dBm Typ. at 900 MHz
- Surface-Mountable Plastic Package

Applications

- Cellular Systems
- Multi-Carrier Applications

Electrical Specifications at Ta = 25C

Symbol	Parameters: Test Conditions: Z ₀ = 50 Ohms, f = 800-1000 MHz		Units	Min.	Тур.	Max.
P _{1dB}	Output Power at 1dB Compression	f = 800-1000 MHz	dBm		24.0	
S ₂₁	Power Gain	f = 800-1000 MHz	dB		14.5	
S ₁₂	Reverse Isolation	f = 800-1000 MHz	dB		30.0	
VSWR	Input VSWR	f = 800-1000 MHz	-		2.0:1	
VSWR	Output VSWR	f = 800-1000 MHz	-		2.0:1	
IP ₃	Third Order Intercept Point	f = 800-1000 MHz	dBm		42.0	
NF	Noise Figure	f = 800-1000 MHz	dB		5.0	·
I _d	Device Current	Vc=+5V	mA		110.0	


The information provided herein is believed to be reliable at press time. Stanford Microdevices assumes no responsibility for inaccuracies or omissions. Stanford Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Stanford Microdevices does not authorize or warrant any Stanford Microdevices product for use in life-support devices and/or systems.


Copyright 1998 Stanford Microdevices, Inc. All worldwide rights reserved.




SXL-189 800-1000 MHz Power MMIC Amplifier

Typical Performance at 25° C (Vc = 5.0V, Ic=110mA)








Pin assignments shown for reference only, not marked on part



LOG 10dB/

Typical Third Order Intercept Point Performance at 900 MHz



CENTER 900.00 MHz

SPAN 5.00 MHz

Tone Power= +11dBm, IP3 = +42.3dBm



Absolute Maximum Ratings

Parameter	Absolute Maximum			
Device Voltage	7V			
Device Current	200mA			
Power Dissipation	1500mW			
RF Input Power	100mW			
Junction Temperature	+150C			
Operating Temperature	-45C to +85C			
Storage Temperature	-65C to +150C			

Notes:

1. Operation of this device above any one of these parameters may cause permanent damage.

MTTF vs. Temperature @ Id = 110mA

Lead Temperature	Junction Temperature	MTTF (hrs)	
+25C	+90C	>10,000,000	
+60C	+125C	>5,000,000	
+85C	+150C	1,000,000	

Thermal Resistance (Lead-Junction): 60° C/W


Preliminary

SXL-189 800-1000 MHz Power MMIC Amplifier

Part Number Ordering Information

Part Number	Devices Per Reel	Reel Size
SXL-189-TR1	500	7"
SXL-189-TR2	1000	13"
SXL-189-EB	Eval Board	-

Application Schematic and Bias Circuit for 900 MHz Operation



Board Layout and Matching Circuit at 900 MHz

