# S1C17601



# Low Power 16-bit Single Chip Microcontroller

- Low Power MCU (operating voltage 1.8 V, 0.6 μA/SLEEP, 2.0 μA/HALT)
- Flash memory(32KByte), 8.2MHz high speed operating at 1.8V power voltage
- LCD driver: max 128 segment, 16seg x 8com or 20seg x 4com
- Analog I/F: A/D converter(INL/DNL Max. 1.5LSB), R/F converter
- S1C17 High Performance 16-bit RISC CPU Core with C Optimized Compact Code and Serial ICE Support

### **■ DESCRIPTIONS**

The S1C17601 is a 16-bit MCU featuring high-speed low-power operations, compact dimensions, wide address space and on-chip ICE. A/D converter and R/F converter are built in and sensor of various analog I/F can be connected. It is suitable for the application of health care product, sports watch and meter module etc. with sensor that is required a small size and micro display in the battery driven.

### **■ FEATURES**

Power consumption

<b>—</b> 1 <b>—</b> 7 1 <b>0</b> 1 1 <b>—</b> 0		
●CPU	Epson original 16-bit RISC CPU core S1C17 16 bit x 16 bit + 32 bit product-sum operation, 16 bit ÷ 16 bit division arithmetic unit	
●IOSC oscillator circuit	2.7 MHz (typ.) Oscillating start up 5 µs (max.) Boot Clock (External components not required.)	
<ul><li>OSC3 oscillator circuit</li></ul>	Crystal oscillator circuit or ceramic oscillator circuit, 8.2 MHz (max.) or external clock input	
<ul> <li>OSC1 oscillator circuit</li> </ul>	Crystal oscillator circuit 32.768 kHz (typ.)	
Internal flash memory	32 Kbytes (for both instructions and data) Allows 1,000 rewrites (min.) Read/write protection function	
	Allows onboard rewriting with the ICD Mini (S5U1C17702H) debug tool and self-rewriting	
•	via software.	
Internal RAM	2 Kbytes	
Internal Display RAM	20 bytes	
● A/D Converter	10 bit resolution 4ch	
● R/F Converter	DC oscillation/AC oscillation/External input 1ch.	
<ul><li>Input/output port</li></ul>	Max. 24-bit general purpose input/output (shared with peripheral circuit input/output pins)	
Serial interfaces	SPI (master/slave)	1ch
	I <sup>2</sup> C (master)	1ch
	I <sup>2</sup> C (slave)	1ch
<b>●</b> T:	UART (460,800 bps, IrDA1.0 compatible)	1ch
● Timers	8-bit timer (T8F) 16-bit timer (T16)	1ch 3ch
	PWM timer (T16E)	1ch
	8-bit OSC1 timer (T8OSC1)	1ch
	Clock timer (CT)	1ch
	Stopwatch timer (SWT)	1ch
	Watchdog timer (WDT)	1ch
■LCD Driver	16 SEG x 8 COM or 20 SEG x 4 COM (1/3 bias)	
	Internal booster power supply circuit (16-value programmable contrast)	
<ul><li>Supply voltage detector</li></ul>	15-value programmable (1.8 V to 3.2 V)	
<ul><li>Interrupts</li></ul>	NMI, P Port Input interrupt	3ch.
·	Serial Interface interrupt	4ch.
	Timer interrupt	9ch.
	LCD, SVD, ADC, RFC interrupt	
<ul><li>Power supply voltage</li></ul>	1.8 V to 3.6 V (for normal operations)	
	2.7 V to 3.6 V (for flash deletion/programing)	
	Including voltage regulator circuit (with binary prog	grammable operating voltage)
Operating temperature	-25°C to 70°C	

0.6 µA typ. (OSC1=OFF, IOSC=OFF, OSC3=OFF)

SLEEP mode:

# S1C17601

HALT mode: 2.0 μA typ. (OSC1=32 kHz, IOSC=OFF, OSC3=OFF, PCKEN=0x0,

LCD OFF)

 $2.7~\mu A$  typ. (OSC1=32 kHz, IOSC=OFF, OSC3=OFF, PCKEN=0x0,

LCD ON (All LCD On, maximum contrast, VC2 standard)

When operating: 12 µA typ. (OSC1= 32kHz, IOSC=OFF, OSC3=OFF, LCD OFF)


340 µA typ.(OSC1=OFF, IOSC=OFF, OSC3=1 MHz ceramic oscillator)

● Shipping form TQFP13-64 package (10 mm x 10 mm body, 0.5 mm pitch)

VFBGA8H-81 package (8 mm x 8 mm, body, 0.8 mm pitch)

Bare chip 100 µm pitch

## ■ Block Diagram



### NOTICE:

No part of this material may be reproduced or duplicated in any form or by any means without the written permission of Seiko Epson. Seiko Epson reserves the right to make changes to this material without notice. Seiko Epson does not assume any liability of any kind arising out of any inaccuracies contained in this material or due to its application or use in any product or circuit and, further, there is no representation that this material is applicable to products requiring high level reliability, such as, medical products. Moreover, no license to any intellectual property rights is granted by implication or otherwise, and there is no representation or warranty that anything made in accordance with this material will be free from any patent or copyright infringement of a third party. This material or portions thereof may contain technology or the subject relating to strategic products under the control of the Foreign Exchange and Foreign Trade Law of Japan and may require an export license from the Ministry of Economy, Trade and Industry or other approval from another government agency.

All brands or product names mentioned herein are trademarks and/or registered trademarks of their respective companies.

©Seiko Epson Corporation 2009, All rights reserved.

\* This product uses SuperFlash® Technology licensed from Silicon Storage Technology, Inc.

#### **SEIKO EPSON CORPORATION**

SEMICONDUCTOR OPERATIONS DIVISION

IC Sales Department IC International Sales Group

421-8 Hino, Hino-shi, Tokyo 191-8501, JAPAN Phone: 042-587-5814 FAX: 042-587-5117

#### ■ Epson semiconductor website

http://www.epson.jp/device/semicon\_e/

Document code: 410954302 First issue Oct, 2009